

UNIS S10600X-G 系列交换机

单板与光模块适配关系表

Copyright © 2025 紫光恒越技术有限公司及其许可者版权所有，保留一切权利。

非经本公司书面许可，任何单位和个人不得擅自摘抄、复制本文档内容的部分或全部，并不得以任何形式传播。

UNIS 为紫光恒越技术有限公司的商标。对于本手册中出现的其它公司的商标、产品标识及商品名称，由各自权利人拥有。
本文档中的信息可能变动，恕不另行通知。

1 单板与光模块适配关系

本系列产品支持多种光模块或线缆，不同接口支持的光模块或线缆类型不同，具体请参见单板与光模块适配关系表。

电缆仅用于本系列交换机之间互连，作为交换机部分软件特性（如：IRF）的专用线缆。

更多光模块或线缆属性信息，请参见《UNIS 光模块手册》。

1.1 使用限制

拆分后的光接口不支持通过 `speed` 命令修改端口速率。

100GE 的光接口拆分为 10GE，只能使用 QSFP+ to SFP+ 线缆。

1.2 单板与光模块适配关系表

表1-1 单板与光模块适配关系表

单板名称	端口	支持的光模块	说明
LSEM1CGQ16SF0-Z	1~16	LSWM1QSTK0	E7752P06
		LSWM1QSTK1	E7752P06
		LSWM1QSTK2	E7752P06
		LSWM1QSTK3	E7752P06
		LSWM1QSTK4	E7752P06
		LSWM1QSTK5	E7752P06
		QSFP-100G-4SFP-25G-CAB-1M	E7752P06
		QSFP-100G-4SFP-25G-CAB-1M-Z	E7752P06
		QSFP-100G-4SFP-25G-CAB-3M	E7752P06
		QSFP-100G-4SFP-25G-CAB-3M-Z	E7752P06
		QSFP-100G-4SFP-25G-CAB-5M	E7752P06
		QSFP-100G-4SFP-25G-CAB-5M-Z	E7752P06
		QSFP-100G-BIDI-MM850	R7755P01
		QSFP-100G-BIDI-MM850-Z	R7755P01
		QSFP-100G-CWDM4-SM1300-A	E7752P06
		QSFP-100G-D-AOC-10M	E7751P03
		QSFP-100G-D-AOC-10M-H	R7755P01
		QSFP-100G-D-AOC-20M	E7751P03
		QSFP-100G-D-AOC-20M-H	R7755P01

单板名称	端口	支持的光模块	说明
		QSFP-100G-D-AOC-7M	E7752P06
		QSFP-100G-D-AOC-7M-H	R7755P01
		QSFP-100G-D-CAB-1M	E7752P06
		QSFP-100G-D-CAB-1M-Z	E7752P06
		QSFP-100G-D-CAB-3M	E7752P06
		QSFP-100G-D-CAB-3M-Z	E7752P06
		QSFP-100G-D-CAB-5M	E7752P06
		QSFP-100G-D-CAB-5M-Z	E7752P06
		QSFP-100G-ER4L-WDM1300	E7752P06
		QSFP-100G-ER4L-WDM1300-Z	E7752P06
		QSFP-100G-eSR4-MM850	E7752P06
		QSFP-100G-LR4L-WDM1300	E7752P06
		QSFP-100G-LR4L-WDM1300-Z	E7752P06
		QSFP-100G-LR4-WDM1300	E7752P06
		QSFP-100G-LR4-WDM1300-Z	E7752P06
		QSFP-100G-PSM4-SM1310	E7752P06
		QSFP-100G-SR4-MM850	E7752P06
		QSFP-100G-SR4-MM850-A	E7752P06
		QSFP-100G-SR4-MM850-H	E775303
		QSFP-100G-SR4-MM850-Z	E7752P06
		QSFP-100G-SWDM4-MM850	E7752P06
		QSFP-100G-SWDM4-MM850-Z	E7752P06
		QSFP-40G-4SFP-10G-CAB-1M-Z	E7752P06
		QSFP-40G-4SFP-10G-CAB-3M-Z	E7752P06
		QSFP-40G-4SFP-10G-CAB-5M-Z	E7752P06
		QSFP-40G-BIDI-SR-MM850	E7752P06
		QSFP-40G-BIDI-SR-MM850-Z	E7752P06
		QSFP-40G-BIDI-WDM850	E7752P06
		QSFP-40G-CSR4-MM850	E7752P06
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	E7752P06
		QSFP-40G-D-AOC-10M	E7752P06

单板名称	端口	支持的光模块	说明
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7752P06
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7752P06
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-D-CAB-1M-Z	E7752P06
		QSFP-40G-D-CAB-3M-Z	E7752P06
		QSFP-40G-D-CAB-5M-Z	E7752P06
		QSFP-40G-ER4-WDM1300	E7752P06
		QSFP-40G-ER4-WDM1300-Z	E7752P06
		QSFP-40G-LR4L-WDM1300	E7752P06
		QSFP-40G-LR4L-WDM1300-Z	E7752P06
		QSFP-40G-LR4-PSM1310	E7752P06
		QSFP-40G-LR4-WDM1300	E7752P06
		QSFP-40G-LR4-WDM1300-Z	E7752P06
		QSFP-40G-SR4-MM850	E7752P06
		QSFP-40G-SR4-MM850-H	E7755
		QSFP-40G-SR4-MM850-Z	E7752P06
LSEM1CGQ36SF0-Z	1~36	LSWM1QSTK0	E7754P02
		LSWM1QSTK1	E7754P02
		LSWM1QSTK2	E7754P02
		LSWM1QSTK3	E7754P02
		LSWM1QSTK4	E7754P02
		LSWM1QSTK5	E7754P02
		QSFP-100G-4SFP-25G-CAB-1M	E7754P02
		QSFP-100G-4SFP-25G-CAB-3M	E7754P02
		QSFP-100G-4SFP-25G-CAB-5M	E7754P02
		QSFP-100G-BIDI-MM850	R7755P01
		QSFP-100G-BIDI-MM850-Z	R7755P01
		QSFP-100G-CWDM4-SM1300-A	E7754P02
		QSFP-100G-D-AOC-10M	E7753P15
		QSFP-100G-D-AOC-10M-H	R7755P01

单板名称	端口	支持的光模块	说明
		QSFP-100G-D-AOC-20M	E7753P15
		QSFP-100G-D-AOC-20M-H	R7755P01
		QSFP-100G-D-AOC-7M	E7754P02
		QSFP-100G-D-AOC-7M-H	R7755P01
		QSFP-100G-D-CAB-1M	E7754P02
		QSFP-100G-D-CAB-1M-Z	E7754P02
		QSFP-100G-D-CAB-3M	E7754P02
		QSFP-100G-D-CAB-3M-Z	E7754P02
		QSFP-100G-D-CAB-5M	E7754P02
		QSFP-100G-D-CAB-5M-Z	E7754P02
		QSFP-100G-eSR4-MM850	E7754P02
		QSFP-100G-LR4L-WDM1300	E7754P02
		QSFP-100G-LR4L-WDM1300-Z	E7754P02
		QSFP-100G-LR4-WDM1300	E7754P02
		QSFP-100G-LR4-WDM1300-Z	E7754P02
		QSFP-100G-PSM4-SM1310	E7754P02
		QSFP-100G-SR4-MM850	E7754P02
		QSFP-100G-SR4-MM850-A	E7754P02
		QSFP-100G-SR4-MM850-H	E7754P03
		QSFP-100G-SR4-MM850-Z	E7754P02
		QSFP-100G-SWDM4-MM850	E7754P02
		QSFP-100G-SWDM4-MM850-Z	E7754P02
		QSFP-40G-4SFP-10G-CAB-1M-Z	E7754P02
		QSFP-40G-4SFP-10G-CAB-3M-Z	E7754P02
		QSFP-40G-4SFP-10G-CAB-5M-Z	E7754P02
		QSFP-40G-BIDI-SR-MM850	E7754P02
		QSFP-40G-BIDI-SR-MM850-Z	E7754P02
		QSFP-40G-BIDI-WDM850	E7754P02
		QSFP-40G-CSR4-MM850	E7754P02
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	E7754P02
		QSFP-40G-D-AOC-10M	E7754P02

单板名称	端口	支持的光模块	说明
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7754P02
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7754P02
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-D-CAB-1M-Z	E7754P02
		QSFP-40G-D-CAB-3M-Z	E7754P02
		QSFP-40G-D-CAB-5M-Z	E7754P02
		QSFP-40G-ER4-WDM1300	E7754P02
		QSFP-40G-ER4-WDM1300-Z	E7754P02
		QSFP-40G-LR4L-WDM1300	E7754P02
		QSFP-40G-LR4L-WDM1300-Z	E7754P02
		QSFP-40G-LR4-PSM1310	E7754P02
		QSFP-40G-LR4-PSM1310-A	E7754P02
		QSFP-40G-LR4-WDM1300	E7754P02
		QSFP-40G-LR4-WDM1300-Z	E7754P02
		QSFP-40G-SR4-MM850	E7754P02
		QSFP-40G-SR4-MM850-H	E7755
		QSFP-40G-SR4-MM850-Z	E7754P02
LSEM1GT48TS24QSSD0-Z	49~72	CAB-0.5M-SFP+	E7754P02, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		CAB-1M-SFP+	E7754P02, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.

单板名称	端口	支持的光模块	说明
		CAB-3M-SFP+	E7754P02,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		LSTM1STK	E7754P02,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		LSWM1STK	E7754P02,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		LSWM2STK	E7754P02,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		LSWM3STK	E7754P02,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		SFP-10G-D-CAB-1M-Z	E7754P02,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.

单板名称	端口	支持的光模块	说明
		SFP-10G-D-CAB-3M-Z	E7754P02, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		SFP-10G-D-CAB-5M-Z	E7754P02, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	E7754P02
		SFP-FE-LX-SM1310-A	E7754P02
		SFP-FE-LX-SM1310-A-Z	E7754P02
		SFP-FE-LX-SM1310-BIDI	E7754P02
		SFP-FE-LX-SM1310-D	E7754P02
		SFP-FE-LX-SM1550-BIDI	E7754P02
		SFP-FE-SX-MM1310-A	E7754P02
		SFP-GE-LH100-SM1550	E7754P02
		SFP-GE-LH40-SM1310	E7754P02
		SFP-GE-LH40-SM1310-A-Z	E7754P02
		SFP-GE-LH40-SM1310-BIDI	E7754P02
		SFP-GE-LH40-SM1310-D	E7754P02
		SFP-GE-LH40-SM1550	E7754P02
		SFP-GE-LH40-SM1550-BIDI	E7754P02
		SFP-GE-LH70-SM1490-BIDI	E7754P02
		SFP-GE-LH70-SM1550-BIDI	E7754P02
		SFP-GE-LH80-SM1550	E7754P02
		SFP-GE-LH80-SM1550-D	E7754P02
		SFP-GE-LH80-SM1550-Z	E7754P02
		SFP-GE-LX-SM1310-A	E7754P02
		SFP-GE-LX-SM1310-A-Z	E7754P02

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1310-BIDI	E7754P02
		SFP-GE-LX-SM1310-D	E7754P02
		SFP-GE-LX-SM1310-S	E7754P02
		SFP-GE-LX-SM1490-BIDI	E7754P02
		SFP-GE-SX-MM850-A	E7754P02
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7754P02
		SFP-GE-SX-MM850-D	E7754P02
		SFP-GE-SX-MM850-S	E7754P02
		SFP-GE-T	E7754P02
		SFP-GE-T-D	E7754P02
		SFP-GE-T-Z	E7754P02
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7754P02
		SFP-XG-LH40-SM1330-BIDI	E7754P02
		SFP-XG-LH40-SM1550	E7754P02
		SFP-XG-LH40-SM1550-D	E7754P02
		SFP-XG-LH40-SM1550-Z	E7754P02
		SFP-XG-LH80-SM1490-BIDI	E7754P02
		SFP-XG-LH80-SM1550	E7754P02
		SFP-XG-LH80-SM1550-A-Z	E7754P02
		SFP-XG-LH80-SM1550-BIDI	E7754P02
		SFP-XG-LH80-SM1550-D	E7754P02
		SFP-XG-LX-SM1270-BIDI	E7754P02
		SFP-XG-LX-SM1310	E7754P02
		SFP-XG-LX-SM1310-D	E7754P02
		SFP-XG-LX-SM1310-E	E7754P02
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02

单板名称	端口	支持的光模块	说明
		SFP-XG-LX-SM1310-E-Z	E7754P02
		SFP-XG-LX-SM1330-BIDI	E7754P02
		SFP-XG-SX-MM850-A	E7754P02
		SFP-XG-SX-MM850-D	E7754P02
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7754P02
		SFP-XG-SX-MM850-E	E7754P02
		SFP-XG-SX-MM850-F1	E7754P02
		SFP-XG-SX-MM850-H	E7755
	73~74	LSWM1QSTK0	E7754P02, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM1QSTK1	E7754P02, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM1QSTK2	E7754P02, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM1QSTK3	E7754P02
		LSWM1QSTK4	E7754P02
		LSWM1QSTK5	E7754P02
		QSFP-40G-4SFP-10G-CAB-1M-Z	E7754P02
		QSFP-40G-4SFP-10G-CAB-3M-Z	E7754P02
		QSFP-40G-4SFP-10G-CAB-5M-Z	E7754P02
		QSFP-40G-BIDI-SR-MM850	E7754P02

单板名称	端口	支持的光模块	说明
		QSFP-40G-BIDI-SR-MM850-Z	E7754P02
		QSFP-40G-BIDI-WDM850	E7754P02
		QSFP-40G-CSR4-MM850	E7754P02
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	E7754P02
		QSFP-40G-D-AOC-10M	E7754P02
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7754P02
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7754P02
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-ER4-WDM1300	E7754P02
		QSFP-40G-ER4-WDM1300-Z	E7754P02
		QSFP-40G-LR4L-WDM1300	E7754P02
		QSFP-40G-LR4L-WDM1300-Z	E7754P02
		QSFP-40G-LR4-PSM1310	E7754P02
		QSFP-40G-LR4-WDM1300	E7754P02
		QSFP-40G-LR4-WDM1300-Z	E7754P02
		QSFP-40G-SR4-MM850	E7754P02
		QSFP-40G-SR4-MM850-H	E7755
		QSFP-40G-SR4-MM850-Z	E7754P02
LSEM1GT48TSSD0-Z	49~52	CAB-0.5M-SFP+	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		CAB-1M-SFP+	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.

单板名称	端口	支持的光模块	说明
		CAB-3M-SFP+	E7752P06,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		LSTM1STK	E7752P06,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		LSWM1STK	E7752P06,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		LSWM2STK	E7752P06,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		LSWM3STK	E7752P06,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		SFP-10G-D-CAB-1M-Z	E7752P06,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.

单板名称	端口	支持的光模块	说明
		SFP-10G-D-CAB-3M-Z	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		SFP-10G-D-CAB-5M-Z	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	R7755P01
		SFP-FE-LX-SM1310-A	E775305
		SFP-FE-LX-SM1310-A-Z	E7752P06
		SFP-FE-LX-SM1310-BIDI	E775305
		SFP-FE-LX-SM1310-D	E775305
		SFP-FE-LX-SM1550-BIDI	E775305
		SFP-FE-SX-MM1310-A	E775305
		SFP-GE-LH100-SM1550	E7752P06
		SFP-GE-LH40-SM1310	E7752P06
		SFP-GE-LH40-SM1310-A-Z	E7752P06
		SFP-GE-LH40-SM1310-BIDI	E7752P06
		SFP-GE-LH40-SM1310-D	E7752P06
		SFP-GE-LH40-SM1550	E7752P06
		SFP-GE-LH40-SM1550-BIDI	E7752P06
		SFP-GE-LH70-SM1490-BIDI	E7752P06
		SFP-GE-LH70-SM1550-BIDI	E7752P06
		SFP-GE-LH80-SM1550	E7752P06
		SFP-GE-LH80-SM1550-D	E7752P06
		SFP-GE-LH80-SM1550-Z	E7752P06
		SFP-GE-LX-SM1310-A	E7752P06
		SFP-GE-LX-SM1310-A-Z	E7752P06

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1310-BIDI	E7752P06
		SFP-GE-LX-SM1310-D	E7752P06
		SFP-GE-LX-SM1310-S	E7752P06
		SFP-GE-LX-SM1490-BIDI	E7752P06
		SFP-GE-SX-MM850-A	E7752P06
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7752P06
		SFP-GE-SX-MM850-D	E7752P06
		SFP-GE-SX-MM850-S	E7752P06
		SFP-GE-T	E7752P06
		SFP-GE-T-D	E7752P06
		SFP-GE-T-Z	E7752P06
		SFP-XG-D-AOC-10M-H	E7755
		SFP-XG-D-AOC-20M-H	E7755
		SFP-XG-D-AOC-7M-H	E7755
		SFP-XG-LH40-SM1270-BIDI	E7752P06
		SFP-XG-LH40-SM1330-BIDI	E7752P06
		SFP-XG-LH40-SM1550	E7752P06
		SFP-XG-LH40-SM1550-D	E7752P06
		SFP-XG-LH40-SM1550-Z	E7752P06
		SFP-XG-LH80-SM1490-BIDI	E7752P06
		SFP-XG-LH80-SM1550	E7752P06
		SFP-XG-LH80-SM1550-BIDI	E7752P06
		SFP-XG-LH80-SM1550-D	E7752P06
		SFP-XG-LX-SM1270-BIDI	E7752P06
		SFP-XG-LX-SM1310	E7752P06
		SFP-XG-LX-SM1310-D	E7752P06
		SFP-XG-LX-SM1310-E	E7752P06
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7752P06

单板名称	端口	支持的光模块	说明
		SFP-XG-LX-SM1330-BIDI	E7752P06
		SFP-XG-SX-MM850-A	E7752P06
		SFP-XG-SX-MM850-D	E7752P06
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7752P06
		SFP-XG-SX-MM850-E	E7752P06
		SFP-XG-SX-MM850-F1	E7752P06
		SFP-XG-SX-MM850-H	E7755
LSEM1QGS16SF0-Z	1~16	LSWM1QSTK0	E7753P01
		LSWM1QSTK1	E7753P01
		LSWM1QSTK2	E7753P01
		LSWM1QSTK3	E7753P01
		LSWM1QSTK4	E7753P01
		LSWM1QSTK5	E7753P01
		QSFP-40G-4SFP-10G-CAB-1M-Z	E7753P01
		QSFP-40G-4SFP-10G-CAB-3M-Z	E7753P01
		QSFP-40G-4SFP-10G-CAB-5M-Z	E7753P01
		QSFP-40G-BIDI-SR-MM850	E7753P01
		QSFP-40G-BIDI-SR-MM850-Z	E7753P01
		QSFP-40G-BIDI-WDM850	E7753P01
		QSFP-40G-CSR4-MM850	E7753P01
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	E7753P01
		QSFP-40G-D-AOC-10M	E7753P01
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7753P01
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7753P01
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-D-CAB-1M-Z	E7753P01
		QSFP-40G-D-CAB-3M-Z	E7753P01

单板名称	端口	支持的光模块	说明
		QSFP-40G-D-CAB-5M-Z	E7753P01
		QSFP-40G-ER4-WDM1300	E7753P01
		QSFP-40G-ER4-WDM1300-Z	E7753P01
		QSFP-40G-LR4L-WDM1300	E7753P01
		QSFP-40G-LR4L-WDM1300-Z	E7753P01
		QSFP-40G-LR4-PSM1310	E7753P01
		QSFP-40G-LR4-WDM1300	E7753P01
		QSFP-40G-LR4-WDM1300-Z	E7753P01
		QSFP-40G-LX4-WDM1300	R7753P05
		QSFP-40G-LX4-WDM1300-Z	R7753P05
		QSFP-40G-SR4-MM850	E7753P01
		QSFP-40G-SR4-MM850-H	E7755
		QSFP-40G-SR4-MM850-Z	E7753P01
LSEM1SUPA0-Z	MANAGEMENT	SFP-GE-LH100-SM1550	E7752P06
		SFP-GE-LH40-SM1310	E7752P06
		SFP-GE-LH40-SM1310-A-Z	E7752P06
		SFP-GE-LH40-SM1310-D	E7752P06
		SFP-GE-LH40-SM1550	E7752P06
		SFP-GE-LH80-SM1550	E7752P06
		SFP-GE-LH80-SM1550-D	E7752P06
		SFP-GE-LH80-SM1550-Z	E7752P06
		SFP-GE-LX-SM1310-A	E7752P06
		SFP-GE-LX-SM1310-A-Z	E7752P06
		SFP-GE-LX-SM1310-BIDI	E7752P06
		SFP-GE-LX-SM1310-D	E7752P06
		SFP-GE-LX-SM1310-S	E7752P06
		SFP-GE-LX-SM1490-BIDI	E7752P06
		SFP-GE-SX-MM850-A	E7752P06
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7752P06
		SFP-GE-SX-MM850-D	E7752P06

单板名称	端口	支持的光模块	说明
		SFP-GE-SX-MM850-S	E7752P06
LSEM1SUPB0-Z	MANAGEMENT	SFP-GE-LH100-SM1550	E7752P06
		SFP-GE-LH40-SM1310	E7752P06
		SFP-GE-LH40-SM1310-A-Z	E7752P06
		SFP-GE-LH40-SM1310-D	E7752P06
		SFP-GE-LH40-SM1550	E7752P06
		SFP-GE-LH80-SM1550	E7752P06
		SFP-GE-LH80-SM1550-D	E7752P06
		SFP-GE-LH80-SM1550-Z	E7752P06
		SFP-GE-LX-SM1310-A	E7752P06
		SFP-GE-LX-SM1310-A-Z	E7752P06
		SFP-GE-LX-SM1310-BIDI	E7752P06
		SFP-GE-LX-SM1310-D	E7752P06
		SFP-GE-LX-SM1310-S	E7752P06
		SFP-GE-LX-SM1490-BIDI	E7752P06
		SFP-GE-SX-MM850-A	E7752P06
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7752P06
		SFP-GE-SX-MM850-D	E7752P06
		SFP-GE-SX-MM850-S	E7752P06
LSEM1TGS16GP32SD0-Z	1~16,33~48	SFP-FE-LH40-SM1310	E7753P01
		SFP-FE-LX-SM1310-A	E7753P01
		SFP-FE-LX-SM1310-A-Z	E7753P01
		SFP-FE-LX-SM1310-BIDI	E7753P01
		SFP-FE-LX-SM1310-D	E7753P01
		SFP-FE-LX-SM1550-BIDI	E7753P01
		SFP-FE-SX-MM1310-A	E7753P01
		SFP-GE-LH100-SM1550	E7753P01
		SFP-GE-LH40-SM1310	E7753P01
		SFP-GE-LH40-SM1310-BIDI	E7753P01
		SFP-GE-LH40-SM1310-D	E7753P01

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1550	E7753P01
		SFP-GE-LH40-SM1550-BIDI	E7753P01
		SFP-GE-LH70-SM1490-BIDI	E7753P01
		SFP-GE-LH70-SM1550-BIDI	E7753P01
		SFP-GE-LH80-SM1550	E7753P01
		SFP-GE-LH80-SM1550-D	E7753P01
		SFP-GE-LX-SM1310-A	E7753P01
		SFP-GE-LX-SM1310-A-Z	E7753P01
		SFP-GE-LX-SM1310-BIDI	E7753P01
		SFP-GE-LX-SM1310-D	E7753P01
		SFP-GE-LX-SM1310-S	E7753P01
		SFP-GE-LX-SM1490-BIDI	E7753P01
		SFP-GE-SX-MM850-A	E7753P01
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7753P01
		SFP-GE-SX-MM850-D	E7753P01
		SFP-GE-SX-MM850-S	E7753P01
		SFP-GE-T	E7753P01
		SFP-GE-T-D	E7753P01
		SFP-GE-T-Z	E7753P01
17~32		CAB-0.5M-SFP+	E7753P01, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		CAB-1M-SFP+	E7753P01, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.

单板名称	端口	支持的光模块	说明
		CAB-3M-SFP+	E7753P01, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSTM1STK	E7753P01, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM1STK	E7753P01, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM2STK	E7753P01, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM3STK	E7753P01, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		SFP-10G-D-CAB-1M-Z	E7753P01, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.

单板名称	端口	支持的光模块	说明
		SFP-10G-D-CAB-3M-Z	E7753P01, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		SFP-10G-D-CAB-5M-Z	E7753P01, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	E7753P01
		SFP-FE-LX-SM1310-A	E7753P01
		SFP-FE-LX-SM1310-A-Z	E7753P01
		SFP-FE-LX-SM1310-BIDI	E7753P01
		SFP-FE-LX-SM1310-D	E7753P01
		SFP-FE-LX-SM1550-BIDI	E7753P01
		SFP-FE-SX-MM1310-A	E7753P01
		SFP-GE-LH100-SM1550	E7753P01
		SFP-GE-LH40-SM1310	E7753P01
		SFP-GE-LH40-SM1310-BIDI	E7753P01
		SFP-GE-LH40-SM1310-D	E7753P01
		SFP-GE-LH40-SM1550	E7753P01
		SFP-GE-LH40-SM1550-BIDI	E7753P01
		SFP-GE-LH70-SM1490-BIDI	E7753P01
		SFP-GE-LH70-SM1550-BIDI	E7753P01
		SFP-GE-LH80-SM1550	E7753P01
		SFP-GE-LH80-SM1550-D	E7753P01
		SFP-GE-LX-SM1310-A	E7753P01
		SFP-GE-LX-SM1310-A-Z	E7753P01
		SFP-GE-LX-SM1310-BIDI	E7753P01
		SFP-GE-LX-SM1310-D	E7753P01

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1310-S	E7753P01
		SFP-GE-LX-SM1490-BIDI	E7753P01
		SFP-GE-SX-MM850-A	E7753P01
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7753P01
		SFP-GE-SX-MM850-D	E7753P01
		SFP-GE-SX-MM850-S	E7753P01
		SFP-GE-T	E7753P01
		SFP-GE-T-D	E7753P01
		SFP-GE-T-Z	E7753P01
		SFP-XG-D-AOC-10M-H	E7755
		SFP-XG-D-AOC-20M-H	E7755
		SFP-XG-D-AOC-7M-H	E7755
		SFP-XG-LH40-SM1270-BIDI	E7753P01
		SFP-XG-LH40-SM1330-BIDI	E7753P01
		SFP-XG-LH40-SM1550	E7753P01
		SFP-XG-LH40-SM1550-D	E7753P01
		SFP-XG-LH40-SM1550-Z	E7753P01
		SFP-XG-LH80-SM1550	E7753P01
		SFP-XG-LH80-SM1550-D	E7753P01
		SFP-XG-LX-SM1270-BIDI	E7753P01
		SFP-XG-LX-SM1310-D	E7753P01
		SFP-XG-LX-SM1310-E	E7753P01
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7753P01
		SFP-XG-LX-SM1330-BIDI	E7753P01
		SFP-XG-SX-MM850-D	E7753P01
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7753P01

单板名称	端口	支持的光模块	说明
		SFP-XG-SX-MM850-E	E7753P01
		SFP-XG-SX-MM850-F1	E7753P01
		SFP-XG-SX-MM850-H	E7755
LSEM1TGS24SD0-Z	1~24	CAB-0.5M-SFP+	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		CAB-1M-SFP+	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		CAB-3M-SFP+	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSTM1STK	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM1STK	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM2STK	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.

单板名称	端口	支持的光模块	说明
			connections.
		LSWM3STK	E7752P06,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		SFP-10G-D-CAB-1M-Z	E7752P06,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		SFP-10G-D-CAB-3M-Z	E7752P06,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		SFP-10G-D-CAB-5M-Z	E7752P06,In versions earlier than R7760P03,the card cannot be used for IRF setup connections. In R7760P03 or later versions,the card can be used for IRF setup connections.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	R7755P01
		SFP-FE-LX-SM1310-A	R7755P01
		SFP-FE-LX-SM1310-BIDI	R7755P01
		SFP-FE-LX-SM1310-D	R7755P01
		SFP-FE-LX-SM1550-BIDI	R7755P01
		SFP-FE-SX-MM1310-A	R7755P01
		SFP-GE-LH100-SM1550	E7752P06

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1310	E7752P06
		SFP-GE-LH40-SM1310-A-Z	E7752P06
		SFP-GE-LH40-SM1310-BIDI	E7752P06
		SFP-GE-LH40-SM1310-D	E7752P06
		SFP-GE-LH40-SM1550	E7752P06
		SFP-GE-LH40-SM1550-BIDI	E7752P06
		SFP-GE-LH70-SM1490-BIDI	E7752P06
		SFP-GE-LH70-SM1550-BIDI	E7752P06
		SFP-GE-LH80-SM1550	E7752P06
		SFP-GE-LH80-SM1550-D	E7752P06
		SFP-GE-LH80-SM1550-Z	E7752P06
		SFP-GE-LX-SM1310-A	E7752P06
		SFP-GE-LX-SM1310-A-Z	E7752P06
		SFP-GE-LX-SM1310-BIDI	E7752P06
		SFP-GE-LX-SM1310-D	E7752P06
		SFP-GE-LX-SM1310-S	E7752P06
		SFP-GE-LX-SM1490-BIDI	E7752P06
		SFP-GE-SX-MM850-A	E7752P06
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7752P06
		SFP-GE-SX-MM850-D	E7752P06
		SFP-GE-SX-MM850-S	E7752P06
		SFP-GE-T	E7752P06
		SFP-GE-T-D	E7752P06
		SFP-GE-T-Z	E7752P06
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7752P06
		SFP-XG-LH40-SM1330-BIDI	E7752P06
		SFP-XG-LH40-SM1550	E7752P06

单板名称	端口	支持的光模块	说明
		SFP-XG-LH40-SM1550-D	E7752P06
		SFP-XG-LH40-SM1550-Z	E7752P06
		SFP-XG-LH80-SM1490-BIDI	E7752P06
		SFP-XG-LH80-SM1550	E7752P06
		SFP-XG-LH80-SM1550-BIDI	E7752P06
		SFP-XG-LH80-SM1550-D	E7752P06
		SFP-XG-LX-SM1270-BIDI	E7752P06
		SFP-XG-LX-SM1310	E7752P06
		SFP-XG-LX-SM1310-D	E7752P06
		SFP-XG-LX-SM1310-E	E7752P06
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7752P06
		SFP-XG-LX-SM1330-BIDI	E7752P06
		SFP-XG-SX-MM850-A	E7752P06
		SFP-XG-SX-MM850-D	E7752P06
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7752P06
		SFP-XG-SX-MM850-E	E7752P06
		SFP-XG-SX-MM850-F1	E7752P06
		SFP-XG-SX-MM850-H	E7755
LSEM1TGS48QSSF0-Z	1~48	CAB-0.5M-SFP+	E7753P01
		CAB-1M-SFP+	E7753P01
		CAB-3M-SFP+	E7753P01
		LSTM1STK	E7753P01
		LSWM1STK	E7753P01
		LSWM2STK	E7753P01
		LSWM3STK	E7753P01
		SFP-10G-D-CAB-1M-Z	E7753P01
		SFP-10G-D-CAB-3M-Z	E7753P01
		SFP-10G-D-CAB-5M-Z	E7753P01

单板名称	端口	支持的光模块	说明
		SFP-10GE-T	R7756P06, Up to eight interfaces are supported. For an interface inserted with a transceiver module, you cannot insert transceiver modules of the same model into the adjacent interfaces on the top, bottom, left, and right of the interface.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-GE-LH100-SM1550	E7753P01
		SFP-GE-LH40-SM1310	E7753P01
		SFP-GE-LH40-SM1310-BIDI	E7753P01
		SFP-GE-LH40-SM1310-D	E7753P01
		SFP-GE-LH40-SM1550	E7753P01
		SFP-GE-LH40-SM1550-BIDI	E7753P01
		SFP-GE-LH70-SM1490-BIDI	E7753P01
		SFP-GE-LH70-SM1550-BIDI	E7753P01
		SFP-GE-LH80-SM1550	E7753P01
		SFP-GE-LH80-SM1550-D	E7753P01
		SFP-GE-LX-SM1310-A	E7753P01
		SFP-GE-LX-SM1310-A-Z	E7753P01
		SFP-GE-LX-SM1310-BIDI	E7753P01
		SFP-GE-LX-SM1310-D	E7753P01
		SFP-GE-LX-SM1310-S	E7753P01
		SFP-GE-LX-SM1490-BIDI	E7753P01
		SFP-GE-SX-MM850-A	E7753P01
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7753P01
		SFP-GE-SX-MM850-D	E7753P01
		SFP-GE-SX-MM850-S	E7753P01
		SFP-GE-T	E7753P01
		SFP-GE-T-D	E7753P01
		SFP-GE-T-Z	E7753P01

单板名称	端口	支持的光模块	说明
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7753P01
		SFP-XG-LH40-SM1330-BIDI	E7753P01
		SFP-XG-LH40-SM1550	E7753P01
		SFP-XG-LH40-SM1550-D	E7753P01
		SFP-XG-LH40-SM1550-Z	E7753P01
		SFP-XG-LH80-SM1550	E7753P01
		SFP-XG-LH80-SM1550-D	E7753P01
		SFP-XG-LX-SM1270-BIDI	E7753P01
		SFP-XG-LX-SM1310-D	E7753P01
		SFP-XG-LX-SM1310-E	E7753P01
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7753P01
		SFP-XG-LX-SM1310-S	E7753P01
		SFP-XG-LX-SM1330-BIDI	E7753P01
		SFP-XG-SX-MM850-D	E7753P01
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7753P01
		SFP-XG-SX-MM850-E	E7753P01
		SFP-XG-SX-MM850-F1	E7753P01
		SFP-XG-SX-MM850-H	E7755
		SFP-XG-SX-MM850-S	E7753P01
	49~52	LSWM1QSTK0	E7753P01
		LSWM1QSTK1	E7753P01
		LSWM1QSTK2	E7753P01
		LSWM1QSTK3	E7753P01
		LSWM1QSTK4	E7753P01
		LSWM1QSTK5	E7753P01

单板名称	端口	支持的光模块	说明
		QSFP-40G-4SFP-10G-CAB-1M-Z	E7753P01
		QSFP-40G-4SFP-10G-CAB-3M-Z	E7753P01
		QSFP-40G-4SFP-10G-CAB-5M-Z	E7753P01
		QSFP-40G-BIDI-SR-MM850	E7753P01
		QSFP-40G-BIDI-SR-MM850-Z	E7753P01
		QSFP-40G-BIDI-WDM850	E7753P01
		QSFP-40G-CSR4-MM850	E7753P01
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	E7753P01
		QSFP-40G-D-AOC-10M	E7753P01
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7753P01
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7753P01
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-D-CAB-1M-Z	E7753P01
		QSFP-40G-D-CAB-3M-Z	E7753P01
		QSFP-40G-D-CAB-5M-Z	E7753P01
		QSFP-40G-ER4-WDM1300	E7753P01
		QSFP-40G-ER4-WDM1300-Z	E7753P01
		QSFP-40G-LR4L-WDM1300	E7753P01
		QSFP-40G-LR4L-WDM1300-Z	E7753P01
		QSFP-40G-LR4-PSM1310	E7753P01
		QSFP-40G-LR4-WDM1300	E7753P01
		QSFP-40G-LR4-WDM1300-Z	E7753P01
		QSFP-40G-SR4-MM850	E7753P01
		QSFP-40G-SR4-MM850-H	E7755
		QSFP-40G-SR4-MM850-Z	E7753P01
LSEM1TGS48SD0-Z	1~48	CAB-0.5M-SFP+	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup

单板名称	端口	支持的光模块	说明
			connections.
		CAB-1M-SFP+	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		CAB-3M-SFP+	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSTM1STK	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM1STK	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM2STK	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		LSWM3STK	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be

单板名称	端口	支持的光模块	说明
			used for IRF setup connections.
		SFP-10G-D-CAB-1M-Z	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		SFP-10G-D-CAB-3M-Z	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		SFP-10G-D-CAB-5M-Z	E7752P06, In versions earlier than R7760P03, the card cannot be used for IRF setup connections. In R7760P03 or later versions, the card can be used for IRF setup connections.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	R7755P01
		SFP-FE-LX-SM1310-A	R7755P01
		SFP-FE-LX-SM1310-BIDI	R7755P01
		SFP-FE-LX-SM1310-D	R7755P01
		SFP-FE-LX-SM1550-BIDI	R7755P01
		SFP-FE-SX-MM1310-A	R7755P01
		SFP-GE-LH100-SM1550	E7752P06
		SFP-GE-LH40-SM1310	E7752P06
		SFP-GE-LH40-SM1310-A-Z	E7752P06
		SFP-GE-LH40-SM1310-BIDI	E7752P06
		SFP-GE-LH40-SM1310-D	E7752P06
		SFP-GE-LH40-SM1550	E7752P06

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1550-BIDI	E7752P06
		SFP-GE-LH70-SM1490-BIDI	E7752P06
		SFP-GE-LH70-SM1550-BIDI	E7752P06
		SFP-GE-LH80-SM1550	E7752P06
		SFP-GE-LH80-SM1550-D	E7752P06
		SFP-GE-LH80-SM1550-Z	E7752P06
		SFP-GE-LX-SM1310-A	E7752P06
		SFP-GE-LX-SM1310-A-Z	E7752P06
		SFP-GE-LX-SM1310-BIDI	E7752P06
		SFP-GE-LX-SM1310-D	E7752P06
		SFP-GE-LX-SM1310-S	E7752P06
		SFP-GE-LX-SM1490-BIDI	E7752P06
		SFP-GE-SX-MM850-A	E7752P06
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7752P06
		SFP-GE-SX-MM850-D	E7752P06
		SFP-GE-SX-MM850-S	E7752P06
		SFP-GE-T	E7752P06
		SFP-GE-T-D	E7752P06
		SFP-GE-T-Z	E7752P06
		SFP-XG-D-AOC-10M-H	E7755
		SFP-XG-D-AOC-20M-H	E7755
		SFP-XG-D-AOC-7M-H	E7755
		SFP-XG-LH40-SM1270-BIDI	E7752P06
		SFP-XG-LH40-SM1330-BIDI	E7752P06
		SFP-XG-LH40-SM1550	E7752P06
		SFP-XG-LH40-SM1550-D	E7752P06
		SFP-XG-LH40-SM1550-Z	E7752P06
		SFP-XG-LH80-SM1490-BIDI	E7752P06
		SFP-XG-LH80-SM1550	E7752P06
		SFP-XG-LH80-SM1550-BIDI	E7752P06

单板名称	端口	支持的光模块	说明
		SFP-XG-LH80-SM1550-D	E7752P06
		SFP-XG-LX-SM1270-BIDI	E7752P06
		SFP-XG-LX-SM1310	E7752P06
		SFP-XG-LX-SM1310-D	E7752P06
		SFP-XG-LX-SM1310-E	E7752P06
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7752P06
		SFP-XG-LX-SM1330-BIDI	E7752P06
		SFP-XG-SX-MM850-A	E7752P06
		SFP-XG-SX-MM850-D	E7752P06
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7752P06
		SFP-XG-SX-MM850-E	E7752P06
		SFP-XG-SX-MM850-F1	E7752P06
		SFP-XG-SX-MM850-H	E7755
LSEM1YGS48CQSF0-Z	1~48	CAB-0.5M-SFP+	E7752P06
		CAB-1M-SFP+	E7752P06
		CAB-3M-SFP+	E7752P06
		LSTM1STK	E7752P06
		LSWM1STK	E7752P06
		LSWM2STK	E7752P06
		LSWM3STK	E7752P06
		SFP-10G-D-CAB-1M-Z	E7752P06
		SFP-10G-D-CAB-3M-Z	E7752P06
		SFP-10G-D-CAB-5M-Z	E7752P06

单板名称	端口	支持的光模块	说明
		SFP-10GE-T	R7756P06, Up to eight interfaces are supported. For an interface inserted with a transceiver module, you cannot insert transceiver modules of the same model into the adjacent interfaces on the top, bottom, left, and right of the interface.
		SFP-25G-CSR-MM850	R7755P03
		SFP-25G-D-AOC-10M	E7751P03
		SFP-25G-D-AOC-10M-H	E7755
		SFP-25G-D-AOC-20M	E7751P03
		SFP-25G-D-AOC-20M-H	E7755
		SFP-25G-D-AOC-3M	E7752P06
		SFP-25G-D-AOC-5M	E7752P06
		SFP-25G-D-AOC-5M-H	E7755
		SFP-25G-D-AOC-7M	E7751P03
		SFP-25G-D-AOC-7M-H	E7755
		SFP-25G-D-CAB-1M	E7752P06
		SFP-25G-LR-SM1310	E7752P06
		SFP-25G-LR-SM1310-Z	E7752P06
		SFP-25G-SR-MM850	E7752P06
		SFP-25G-SR-MM850-H	E7754P03
		SFP-25G-SR-MM850-Z	E7752P06
		SFP-GE-LH100-SM1550	E7752P06
		SFP-GE-LH40-SM1310	E7752P06
		SFP-GE-LH40-SM1310-A-Z	E7752P06
		SFP-GE-LH40-SM1310-BIDI	E7752P06
		SFP-GE-LH40-SM1310-D	E7752P06
		SFP-GE-LH40-SM1550	E7752P06
		SFP-GE-LH40-SM1550-BIDI	E7752P06
		SFP-GE-LH70-SM1490-BIDI	E7752P06
		SFP-GE-LH70-SM1550-BIDI	E7752P06
		SFP-GE-LH80-SM1550	E7752P06

单板名称	端口	支持的光模块	说明
		SFP-GE-LH80-SM1550-D	E7752P06
		SFP-GE-LH80-SM1550-Z	E7752P06
		SFP-GE-LX-SM1310-A	E7752P06
		SFP-GE-LX-SM1310-A-Z	E7752P06
		SFP-GE-LX-SM1310-BIDI	E7752P06
		SFP-GE-LX-SM1310-D	E7752P06
		SFP-GE-LX-SM1310-S	E7752P06
		SFP-GE-LX-SM1490-BIDI	E7752P06
		SFP-GE-SX-MM850-A	E7752P06
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7752P06
		SFP-GE-SX-MM850-D	E7752P06
		SFP-GE-SX-MM850-S	E7752P06
		SFP-GE-T	E7752P06
		SFP-GE-T-D	E7752P06
		SFP-GE-T-Z	E7752P06
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7752P06
		SFP-XG-LH40-SM1330-BIDI	E7752P06
		SFP-XG-LH40-SM1550	E7752P06
		SFP-XG-LH40-SM1550-D	E7752P06
		SFP-XG-LH40-SM1550-Z	E7752P06
		SFP-XG-LH80-SM1550	E7752P06
		SFP-XG-LH80-SM1550-D	E7752P06
		SFP-XG-LX-SM1270-BIDI	E7752P06
		SFP-XG-LX-SM1310	E7752P06
		SFP-XG-LX-SM1310-D	E7752P06
		SFP-XG-LX-SM1310-E	E7752P06
		SFP-XG-LX-SM1310-E-H-Z	E7756P02

单板名称	端口	支持的光模块	说明
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7752P06
		SFP-XG-LX-SM1330-BIDI	E7752P06
		SFP-XG-SX-MM850-A	E7752P06
		SFP-XG-SX-MM850-D	E7752P06
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7752P06
		SFP-XG-SX-MM850-E	E7752P06
		SFP-XG-SX-MM850-H	E7755
	13~44	SFP-25G-D-CAB-5M	E7752P06
		SFP-25G-D-CAB-5M-Z	E7752P06
	49~52	LSWM1QSTK0	E7752P06
		LSWM1QSTK1	E7752P06
		LSWM1QSTK2	E7752P06
		LSWM1QSTK3	E7752P06
		LSWM1QSTK4	E7752P06
		LSWM1QSTK5	E7752P06
		QSFP-100G-4SFP-25G-CAB-1M	E7752P06
		QSFP-100G-4SFP-25G-CAB-1M-Z	E7752P06
		QSFP-100G-4SFP-25G-CAB-3M	E7752P06
		QSFP-100G-4SFP-25G-CAB-3M-Z	E7752P06
		QSFP-100G-BIDI-MM850	R7756P07
		QSFP-100G-BIDI-MM850-Z	R7756P07
		QSFP-100G-CWDM4-SM1300-A	E7752P06
		QSFP-100G-D-AOC-10M	E7751P03
		QSFP-100G-D-AOC-10M-H	R7755P01
		QSFP-100G-D-AOC-20M	E7751P03
		QSFP-100G-D-AOC-20M-H	R7755P01
		QSFP-100G-D-AOC-7M	E7752P06
		QSFP-100G-D-AOC-7M-H	R7755P01
		QSFP-100G-D-CAB-1M	E7752P06

单板名称	端口	支持的光模块	说明
		QSFP-100G-D-CAB-1M-Z	E7752P06
		QSFP-100G-D-CAB-3M	E7752P06
		QSFP-100G-D-CAB-3M-Z	E7752P06
		QSFP-100G-ER4L-WDM1300	E7752P06
		QSFP-100G-ER4L-WDM1300-Z	E7752P06
		QSFP-100G-eSR4-MM850	E7752P06
		QSFP-100G-LR4L-WDM1300	E7752P06
		QSFP-100G-LR4L-WDM1300-Z	E7752P06
		QSFP-100G-LR4-WDM1300	E7752P06
		QSFP-100G-LR4-WDM1300-Z	E7752P06
		QSFP-100G-PSM4-SM1310	E7752P06
		QSFP-100G-SR4-MM850	E7752P06
		QSFP-100G-SR4-MM850-A	E7752P06
		QSFP-100G-SR4-MM850-H	E775303
		QSFP-100G-SR4-MM850-Z	E7752P06
		QSFP-100G-SWDM4-MM850	E7752P06
		QSFP-100G-SWDM4-MM850-Z	E7752P06
		QSFP-40G-4SFP-10G-CAB-1M-Z	E7752P06
		QSFP-40G-4SFP-10G-CAB-3M-Z	E7752P06
		QSFP-40G-4SFP-10G-CAB-5M-Z	E7752P06
		QSFP-40G-BIDI-SR-MM850	E7752P06
		QSFP-40G-BIDI-SR-MM850-Z	E7752P06
		QSFP-40G-BIDI-WDM850	E7752P06
		QSFP-40G-CSR4-MM850	E7752P06
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	E7752P06
		QSFP-40G-D-AOC-10M	E7752P06
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7752P06
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7752P06
		QSFP-40G-D-AOC-7M-H	R7755P01

单板名称	端口	支持的光模块	说明
		QSFP-40G-D-CAB-1M-Z	E7752P06
		QSFP-40G-D-CAB-3M-Z	E7752P06
		QSFP-40G-D-CAB-5M-Z	E7752P06
		QSFP-40G-ER4-WDM1300	E7752P06
		QSFP-40G-ER4-WDM1300-Z	E7752P06
		QSFP-40G-LR4L-WDM1300	E7752P06
		QSFP-40G-LR4L-WDM1300-Z	E7752P06
		QSFP-40G-LR4-PSM1310	E7752P06
		QSFP-40G-LR4-WDM1300	E7752P06
		QSFP-40G-LR4-WDM1300-Z	E7752P06
		QSFP-40G-SR4-MM850	E7752P06
		QSFP-40G-SR4-MM850-H	E7755
		QSFP-40G-SR4-MM850-Z	E7752P06
	9~48	SFP-25G-D-CAB-3M	E7752P06