

UNIS R9900 路由器

单板与光模块适配关系表

Copyright © 2020 紫光恒越技术有限公司及其许可者版权所有，保留一切权利。

非经本公司书面许可，任何单位和个人不得擅自摘抄、复制本文档内容的部分或全部，并不得以任何形式传播。

UNIS 为紫光恒越技术有限公司的商标。对于本手册中出现的其它公司的商标、产品标识及商品名称，由各自权利人拥有。

本文档中的信息可能变动，恕不另行通知。

本系列产品支持多种光模块或线缆，不同接口支持的光模块或线缆类型不同，具体请参见下表。
更多光模块或线缆属性信息，请参见《UNIS光模块手册》。

单板名称	端口	支持的光模块	说明
MIC-CLP4L	1-4	SFP-FE-LX-SM1310-A-Z	
MIC-CP1L	1	CFP-100G-ER4-WDM1300	
		CFP-100G-LR4-WDM1300-A	
MIC-GP10L-V2	1-10	SFP-FE-LX-SM1310-A-Z	
		SFP-GE-LX-SM1310-A-Z	
		SFP-GE-SX-MM850-A-Z	
		SFP-GE-T-Z	
MIC-GP20L	1-20	SFP-FE-LX-SM1310-A-Z	
		SFP-GE-LX-SM1310-A-Z	
		SFP-GE-SX-MM850-A-Z	
		SFP-GE-T-Z	
MIC-GP4L	1-4	SFP-FE-LX-SM1310-A-Z	
		SFP-GE-LX-SM1310-A-Z	
		SFP-GE-SX-MM850-A-Z	
MIC-PSP4L	1-4	SFP-2.5G-LX-SM1310-Z	
MIC-SP4L	1-4	SFP-622M-LH40-SM1310	
		SFP-FE-LX-SM1310-A-Z	
MIC-SP8L	1-8	SFP-FE-LX-SM1310-A-Z	
MIC-TCP8L	1-8	SFP-FE-LX-SM1310-A-Z	
MIC-XP2L-LAN	1-2	SFP-GE-LX-SM1310-A-Z	
		SFP-GE-SX-MM850-A-Z	
		SFP-GE-T-Z	
		SFP-XG-LH40-SM1550-Z	
		SFP-XG-LX-SM1310-E-Z	
		SFP-XG-SX-MM850-D-Z	
MIC-XP2L	1-2	SFP-GE-LX-SM1310-A-Z	
		SFP-GE-SX-MM850-A-Z	
		SFP-GE-T-Z	
		SFP-XG-LH40-SM1550-Z	
		SFP-XG-LX-SM1310-E-Z	

单板名称	端口	支持的光模块	说明
		SFP-XG-SX-MM850-D-Z	
MIC-XP4L1	1-4	SFP-GE-LX-SM1310-A-Z	
		SFP-GE-SX-MM850-A-Z	
		SFP-GE-T-Z	
		SFP-XG-LH40-SM1550-Z	
		SFP-XG-LX-SM1310-E-Z	
		SFP-XG-SX-MM850-D-Z	
MIC-XP5L	1-5	SFP-XG-LH40-SM1550-Z	
		SFP-XG-LX-SM1310-E-Z	
		SFP-XG-SX-MM850-D-Z	
	2-5	SFP-GE-LX-SM1310-A-Z	
		SFP-GE-SX-MM850-A-Z	
		SFP-GE-T-Z	
PIC-PSP4L	1-4	SFP-2.5G-LX-SM1310-Z	
PIC-PUP1L	1	XFP-POS-LH10-SM1310-Z	
PIC-TCP8L	1-8	SFP-GE-LX-SM1310-A-Z	
		SFP-GE-SX-MM850-A-Z	
		SFP-GE-T-Z	
SPC-GP44XP4LCX	1-44	SFP-FE-LX-SM1310-A-Z	
		SFP-GE-LX-SM1310-A-Z	
		SFP-GE-SX-MM850-A-Z	
		SFP-GE-T-Z	
	45-48	SFP-XG-LX-SM1310-E-Z	
		SFP-XG-SX-MM850-D-Z	