

UNIS S8600X-G 系列交换机

单板与光模块适配关系表

Copyright © 2025 紫光恒越技术有限公司及其许可者版权所有，保留一切权利。

非经本公司书面许可，任何单位和个人不得擅自摘抄、复制本文档内容的部分或全部，并不得以任何形式传播。

UNIS 为紫光恒越技术有限公司的商标。对于本手册中出现的其它公司的商标、产品标识及商品名称，由各自权利人拥有。
本文档中的信息可能变动，恕不另行通知。

1 单板与光模块适配关系

本系列产品支持多种光模块或线缆，不同接口支持的光模块或线缆类型不同，具体请参见单板与光模块适配关系表。

电缆仅用于本系列交换机之间互连，作为交换机部分软件特性（如：IRF）的专用线缆。

更多光模块或线缆属性信息，请参见《UNIS 光模块手册》。

1.1 使用限制

拆分后的光接口不支持通过 speed 命令修改端口速率。

100GE 的光接口拆分为 10GE，只能使用 QSFP+ to SFP+ 线缆。

1.2 单板与光模块适配关系表

表1-1 单板与光模块适配关系表

单板名称	端口	支持的光模块	说明
LSCM1MPUS06A0-Z	1	SFP-GE-LH100-SM1550	R7723P01
		SFP-GE-LH40-SM1310	R7723P01
		SFP-GE-LH40-SM1310-D	R7723P01
		SFP-GE-LH40-SM1550	R7723P01
		SFP-GE-LH80-SM1550	R7723P01
		SFP-GE-LH80-SM1550-D	R7723P01
		SFP-GE-LX-SM1310-A	R7723P01
		SFP-GE-LX-SM1310-A-Z	R7734
		SFP-GE-LX-SM1310-BIDI	R7723P01
		SFP-GE-LX-SM1310-D	R7723P01
		SFP-GE-LX-SM1490-BIDI	R7723P01
		SFP-GE-SX-MM850-A	R7723P01
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7734
		SFP-GE-SX-MM850-D	R7723P01
LSCM1QGS8CSSE0-Z	1~4,9~12,5~8	LSWM1QSTK0	R7723P01, Can only be used for IRF/M-LAG setup connections.

单板名称	端口	支持的光模块	说明
		LSWM1QSTK1	R7723P01,Can only be used for IRF/M-LAG setup connections.
		LSWM1QSTK2	R7723P01,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-BIDI-SR-MM850	R7723P01
		QSFP-40G-BIDI-SR-MM850-Z	R7734P05
		QSFP-40G-CSR4-MM850	R7723P01
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	R7734P05
		QSFP-40G-D-AOC-10M	R7723P01
		QSFP-40G-D-AOC-10M-H	E7755
		QSFP-40G-D-AOC-20M	R7723P01
		QSFP-40G-D-AOC-20M-H	E7755
		QSFP-40G-D-AOC-7M	R7723P01
		QSFP-40G-D-AOC-7M-H	E7755
		QSFP-40G-D-CAB-1M-Z	R7743P05 ,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-D-CAB-3M-Z	R7743P05 ,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-D-CAB-5M-Z	R7743P05 ,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-ER4-WDM1300	R7723P01
		QSFP-40G-ER4-WDM1300-Z	R7734P05
		QSFP-40G-LR4L-WDM1300	R7723P01
		QSFP-40G-LR4L-WDM1300-Z	R7734P05
		QSFP-40G-LR4-WDM1300	R7723P01
		QSFP-40G-LR4-WDM1300-Z	R7734P05
		QSFP-40G-SR4-MM850-H	E7755
	5~8	QSFP-100G-D-AOC-10M	E775304
		QSFP-100G-D-AOC-10M-H	E7755
		QSFP-100G-D-AOC-20M	E775304
		QSFP-100G-D-AOC-20M-H	E7755

单板名称	端口	支持的光模块	说明
		QSFP-100G-D-AOC-7M-H	E7755
		QSFP-100G-LR4-WDM1300	R7723P01
		QSFP-100G-LR4-WDM1300-Z	R7734P05
		QSFP-100G-SR4-MM850	R7723P01
		QSFP-100G-SR4-MM850-Z	R7734P05
LSCM1SUP03A0-Z	1	SFP-GE-LH100-SM1550	R7723P01
		SFP-GE-LH40-SM1310	R7723P01
		SFP-GE-LH40-SM1310-D	R7723P01
		SFP-GE-LH40-SM1550	R7723P01
		SFP-GE-LH80-SM1550	R7723P01
		SFP-GE-LH80-SM1550-D	R7723P01
		SFP-GE-LX-SM1310-A	R7723P01
		SFP-GE-LX-SM1310-A-Z	R7734
		SFP-GE-LX-SM1310-BIDI	R7723P01
		SFP-GE-LX-SM1310-D	R7723P01
		SFP-GE-LX-SM1490-BIDI	R7723P01
		SFP-GE-SX-MM850-A	R7723P01
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7734
		SFP-GE-SX-MM850-D	R7723P01
LSCM1TGS48SE0-Z	1~48	CAB-0.5M-SFP+	R7723P01
		CAB-1M-SFP+	R7723P01
		CAB-3M-SFP+	R7723P01
		LSTM1STK	R7723P01
		LSWM1STK	R7723P01
		LSWM2STK	R7723P01
		LSWM3STK	R7723P01
		SFP-10G-D-CAB-1M-Z	R7743P05
		SFP-10G-D-CAB-3M-Z	R7743P05
		SFP-10G-D-CAB-5M-Z	R7743P05
		SFP-2.5G-LX10-SM1310-DR-I	E7756P01

单板名称	端口	支持的光模块	说明
		SFP-GE-LH100-SM1550	R7723P01
		SFP-GE-LH40-SM1310	R7723P01
		SFP-GE-LH40-SM1310-D	R7723P01
		SFP-GE-LH40-SM1550	R7723P01
		SFP-GE-LH80-SM1550	R7723P01
		SFP-GE-LH80-SM1550-D	R7723P01
		SFP-GE-LX-SM1310-A	R7723P01
		SFP-GE-LX-SM1310-A-Z	R7734
		SFP-GE-LX-SM1310-BIDI	R7723P01
		SFP-GE-LX-SM1310-D	R7723P01
		SFP-GE-LX-SM1490-BIDI	R7723P01
		SFP-GE-SX-MM850-A	R7723P01
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7734
		SFP-GE-SX-MM850-D	R7723P01
		SFP-GE-T	R7734
		SFP-GE-T-D	R7734
		SFP-GE-T-Z	R7734
		SFP-XG-LH40-SM1550	R7723P01
		SFP-XG-LH40-SM1550-D	R7723P01
		SFP-XG-LH40-SM1550-Z	R7734
		SFP-XG-LH80-SM1550	R7723P01
		SFP-XG-LH80-SM1550-D	R7723P01
		SFP-XG-LX-SM1310	R7723P01
		SFP-XG-LX-SM1310-D	R7723P01
		SFP-XG-LX-SM1310-E	R7723P01
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7734
		SFP-XG-SX-MM850-A	R7723P01
		SFP-XG-SX-MM850-D	R7723P01

单板名称	端口	支持的光模块	说明
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7734
		SFP-XG-SX-MM850-E	R7723P01
		SFP-XG-SX-MM850-F1	R7723P01
LSCM2CGP24TSSC0-Z	1~8	SFP-FE-LH40-SM1310	R7743P05
		SFP-FE-LX-SM1310-A	R7743P05
		SFP-FE-LX-SM1310-A-Z	R7743P05
		SFP-FE-LX-SM1310-BIDI	R7743P05
		SFP-FE-LX-SM1310-D	R7743P05
		SFP-FE-LX-SM1550-BIDI	R7743P05
		SFP-FE-SX-MM1310-A	R7743P05
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
	25~28	CAB-0.5M-SFP+	R7743P05
		CAB-1M-SFP+	R7743P05
		CAB-3M-SFP+	R7743P05
		LSTM1STK	R7743P05
		LSWM1STK	R7743P05
		LSWM2STK	R7743P05
		LSWM3STK	R7743P05
		SFP-10G-D-CAB-1M-Z	R7743P05
		SFP-10G-D-CAB-3M-Z	R7743P05
		SFP-10G-D-CAB-5M-Z	R7743P05
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02

单板名称	端口	支持的光模块	说明
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
		SFP-XG-D-AOC-10M-H	E7755
		SFP-XG-D-AOC-20M-H	E7755
		SFP-XG-D-AOC-7M-H	E7755
		SFP-XG-LH40-SM1270-BIDI	R7743P05
		SFP-XG-LH40-SM1330-BIDI	R7743P05
		SFP-XG-LH40-SM1550	R7743P05
		SFP-XG-LH40-SM1550-D	R7743P05
		SFP-XG-LH40-SM1550-Z	R7743P05
		SFP-XG-LH80-SM1490-BIDI	R7743P05
		SFP-XG-LH80-SM1550	R7743P05
		SFP-XG-LH80-SM1550-BIDI	R7743P05
		SFP-XG-LH80-SM1550-D	R7743P05
		SFP-XG-LX-SM1270-BIDI	R7743P05
		SFP-XG-LX-SM1310	R7743P05
		SFP-XG-LX-SM1310-D	R7743P05
		SFP-XG-LX-SM1310-E	R7743P05
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7743P05
		SFP-XG-LX-SM1330-BIDI	R7743P05
		SFP-XG-SX-MM850-A	R7743P05
		SFP-XG-SX-MM850-D	R7743P05
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7743P05
		SFP-XG-SX-MM850-E	R7743P05
		SFP-XG-SX-MM850-H	E7755

单板名称	端口	支持的光模块	说明
	9~24	SFP-2.5G-LX10-SM1310-DR-I	E7758
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
	MANAGEMENT	SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
LSCM2CGT24TSSC0-Z	25~28	CAB-0.5M-SFP+	R7743P05
		CAB-1M-SFP+	R7743P05
		CAB-3M-SFP+	R7743P05
		LSTM1STK	R7743P05
		LSWM1STK	R7743P05
		LSWM2STK	R7743P05
		LSWM3STK	R7743P05
		SFP-10G-D-CAB-1M-Z	R7743P05
		SFP-10G-D-CAB-3M-Z	R7743P05
		SFP-10G-D-CAB-5M-Z	R7743P05
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	R7743P05
		SFP-XG-LH40-SM1330-BIDI	R7743P05
		SFP-XG-LH40-SM1550	R7743P05
		SFP-XG-LH40-SM1550-D	R7743P05
		SFP-XG-LH40-SM1550-Z	R7743P05
		SFP-XG-LH80-SM1490-BIDI	R7743P05
		SFP-XG-LH80-SM1550	R7743P05
		SFP-XG-LH80-SM1550-BIDI	R7743P05
		SFP-XG-LH80-SM1550-D	R7743P05
		SFP-XG-LX-SM1270-BIDI	R7743P05
		SFP-XG-LX-SM1310	R7743P05
		SFP-XG-LX-SM1310-D	R7743P05
		SFP-XG-LX-SM1310-E	R7743P05
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7743P05
		SFP-XG-LX-SM1330-BIDI	R7743P05
		SFP-XG-SX-MM850-A	R7743P05
		SFP-XG-SX-MM850-D	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7743P05
		SFP-XG-SX-MM850-E	R7743P05
		SFP-XG-SX-MM850-H	E7755
	MANAGEMENT	SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
LSCM2CTGS12GPSC0-Z	1~16	SFP-FE-LH40-SM1310	R7743P05
		SFP-FE-LX-SM1310-A	R7743P05
		SFP-FE-LX-SM1310-A-Z	R7743P05
		SFP-FE-LX-SM1310-BIDI	R7743P05
		SFP-FE-LX-SM1310-D	R7743P05
		SFP-FE-LX-SM1550-BIDI	R7743P05
		SFP-FE-SX-MM1310-A	R7743P05
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
	17~28	CAB-0.5M-SFP+	R7743P05
		CAB-1M-SFP+	R7743P05
		CAB-3M-SFP+	R7743P05
		LSTM1STK	R7743P05
		LSWM1STK	R7743P05
		LSWM2STK	R7743P05
		LSWM3STK	R7743P05
		SFP-10G-D-CAB-1M-Z	R7743P05
		SFP-10G-D-CAB-3M-Z	R7743P05
		SFP-10G-D-CAB-5M-Z	R7743P05
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
		SFP-XG-D-AOC-10M-H	E7755
		SFP-XG-D-AOC-20M-H	E7755
		SFP-XG-D-AOC-7M-H	E7755
		SFP-XG-LH40-SM1270-BIDI	R7743P05
		SFP-XG-LH40-SM1330-BIDI	R7743P05
		SFP-XG-LH40-SM1550	R7743P05
		SFP-XG-LH40-SM1550-D	R7743P05
		SFP-XG-LH40-SM1550-Z	R7743P05
		SFP-XG-LH80-SM1490-BIDI	R7743P05
		SFP-XG-LH80-SM1550	R7743P05
		SFP-XG-LH80-SM1550-BIDI	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-XG-LH80-SM1550-D	R7743P05
		SFP-XG-LX-SM1270-BIDI	R7743P05
		SFP-XG-LX-SM1310	R7743P05
		SFP-XG-LX-SM1310-D	R7743P05
		SFP-XG-LX-SM1310-E	R7743P05
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7743P05
		SFP-XG-LX-SM1330-BIDI	R7743P05
		SFP-XG-SX-MM850-A	R7743P05
		SFP-XG-SX-MM850-D	R7743P05
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7743P05
		SFP-XG-SX-MM850-E	R7743P05
		SFP-XG-SX-MM850-H	E7755
	MANAGEMENT	SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
LSCM2CTGS12GTSC0-Z	17~28	CAB-0.5M-SFP+	R7743P05
		CAB-1M-SFP+	R7743P05
		CAB-3M-SFP+	R7743P05
		LSTM1STK	R7743P05

单板名称	端口	支持的光模块	说明
		LSWM1STK	R7743P05
		LSWM2STK	R7743P05
		LSWM3STK	R7743P05
		SFP-10G-D-CAB-1M-Z	R7743P05
		SFP-10G-D-CAB-3M-Z	R7743P05
		SFP-10G-D-CAB-5M-Z	R7743P05
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
		SFP-XG-D-AOC-10M-H	E7755
		SFP-XG-D-AOC-20M-H	E7755

单板名称	端口	支持的光模块	说明
		SFP-XG-D-AOC-7M-H	E7755
		SFP-XG-LH40-SM1270-BIDI	R7743P05
		SFP-XG-LH40-SM1330-BIDI	R7743P05
		SFP-XG-LH40-SM1550	R7743P05
		SFP-XG-LH40-SM1550-D	R7743P05
		SFP-XG-LH40-SM1550-Z	R7743P05
		SFP-XG-LH80-SM1490-BIDI	R7743P05
		SFP-XG-LH80-SM1550	R7743P05
		SFP-XG-LH80-SM1550-BIDI	R7743P05
		SFP-XG-LH80-SM1550-D	R7743P05
		SFP-XG-LX-SM1270-BIDI	R7743P05
		SFP-XG-LX-SM1310	R7743P05
		SFP-XG-LX-SM1310-D	R7743P05
		SFP-XG-LX-SM1310-E	R7743P05
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7743P05
		SFP-XG-LX-SM1330-BIDI	R7743P05
		SFP-XG-SX-MM850-A	R7743P05
		SFP-XG-SX-MM850-D	R7743P05
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7743P05
		SFP-XG-SX-MM850-E	R7743P05
		SFP-XG-SX-MM850-H	E7755
	MANAGEMENT	SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
LSCM2GP24GTSC0-Z	13~32	SFP-2.5G-LX10-SM1310-DR-I	E7758
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05

单板名称	端口	支持的光模块	说明
	9~12	SFP-GE-T-Z	R7743P05
		SFP-FE-LH40-SM1310	R7743P05
		SFP-FE-LX-SM1310-A	R7743P05
		SFP-FE-LX-SM1310-A-Z	R7743P05
		SFP-FE-LX-SM1310-BIDI	R7743P05
		SFP-FE-LX-SM1310-D	R7743P05
		SFP-FE-LX-SM1550-BIDI	R7743P05
		SFP-FE-SX-MM1310-A	R7743P05
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
LSCM2GP48SC0-Z	1~32	SFP-FE-LH40-SM1310	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-FE-LX-SM1310-A	R7743P05
		SFP-FE-LX-SM1310-A-Z	R7743P05
		SFP-FE-LX-SM1310-BIDI	R7743P05
		SFP-FE-LX-SM1310-D	R7743P05
		SFP-FE-LX-SM1550-BIDI	R7743P05
		SFP-FE-SX-MM1310-A	R7743P05
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
	33~48	SFP-2.5G-LX10-SM1310-DR-I	E7758

单板名称	端口	支持的光模块	说明
		SFP-FE-LX-SM1310-BIDI	R7755P01,If you install this transceiver module on a card developed and delivered earlier,the system displays a message that the transceiver module is not supported on the card.
		SFP-FE-LX-SM1550-BIDI	R7755P01,If you install this transceiver module on a card developed and delivered earlier,the system displays a message that the transceiver module is not supported on the card.
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05

单板名称	端口	支持的光模块	说明
LSCM2GT24GPSC0-Z	25~32	SFP-2.5G-LX10-SM1310-DR-I	E7758
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
LSCM2GT24GPTSSC0-Z	25~32	SFP-FE-LH40-SM1310	R7743P05
		SFP-FE-LX-SM1310-A	R7743P05
		SFP-FE-LX-SM1310-A-Z	R7743P05
		SFP-FE-LX-SM1310-BIDI	R7743P05
		SFP-FE-LX-SM1310-D	R7743P05
		SFP-FE-LX-SM1550-BIDI	R7743P05
		SFP-FE-SX-MM1310-A	R7743P05
		SFP-GE-LH100-SM1550	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
	33~36,41~48	SFP-2.5G-LX10-SM1310-DR-I	E7758
		SFP-FE-LX-SM1310-BIDI	R7755P01,If you install this transceiver module on a card developed and delivered earlier,the system displays a message that the transceiver module is not supported on the card.
		SFP-FE-LX-SM1550-BIDI	R7755P01,If you install this transceiver module on a card developed and delivered earlier,the system displays a message that the transceiver module is not supported on the card.

单板名称	端口	支持的光模块	说明
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
	37~40	CAB-0.5M-SFP+	R7743P05
		CAB-1M-SFP+	R7743P05
		CAB-3M-SFP+	R7743P05
		LSTM1STK	R7743P05
		LSWM1STK	R7743P05
		LSWM2STK	R7743P05
		LSWM3STK	R7743P05
		SFP-10G-D-CAB-1M-Z	R7743P05
		SFP-10G-D-CAB-3M-Z	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-10G-D-CAB-5M-Z	R7743P05
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
		SFP-XG-D-AOC-10M-H	E7755
		SFP-XG-D-AOC-20M-H	E7755
		SFP-XG-D-AOC-7M-H	E7755
		SFP-XG-LH40-SM1270-BIDI	R7743P05
		SFP-XG-LH40-SM1330-BIDI	R7743P05
		SFP-XG-LH40-SM1550	R7743P05
		SFP-XG-LH40-SM1550-D	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-XG-LH40-SM1550-Z	R7743P05
		SFP-XG-LH80-SM1490-BIDI	R7743P05
		SFP-XG-LH80-SM1550	R7743P05
		SFP-XG-LH80-SM1550-BIDI	R7743P05
		SFP-XG-LH80-SM1550-D	R7743P05
		SFP-XG-LX-SM1270-BIDI	R7743P05
		SFP-XG-LX-SM1310	R7743P05
		SFP-XG-LX-SM1310-D	R7743P05
		SFP-XG-LX-SM1310-E	R7743P05
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7743P05
		SFP-XG-LX-SM1330-BIDI	R7743P05
		SFP-XG-SX-MM850-A	R7743P05
		SFP-XG-SX-MM850-D	R7743P05
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7743P05
		SFP-XG-SX-MM850-E	R7743P05
		SFP-XG-SX-MM850-H	E7755
LSCM2MPUS06AS0-Z	MANAGEMENT	SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
LSCM2TGS16GPSC0-Z	1~24	SFP-FE-LH40-SM1310	R7743P05
		SFP-FE-LX-SM1310-A	R7743P05
		SFP-FE-LX-SM1310-A-Z	R7743P05
		SFP-FE-LX-SM1310-BIDI	R7743P05
		SFP-FE-LX-SM1310-D	R7743P05
		SFP-FE-LX-SM1550-BIDI	R7743P05
		SFP-FE-SX-MM1310-A	R7743P05
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
	25~40	CAB-0.5M-SFP+	R7743P05
		CAB-1M-SFP+	R7743P05
		CAB-3M-SFP+	R7743P05
		LSTM1STK	R7743P05
		LSWM1STK	R7743P05
		LSWM2STK	R7743P05
		LSWM3STK	R7743P05
		SFP-10G-D-CAB-1M-Z	R7743P05
		SFP-10G-D-CAB-3M-Z	R7743P05
		SFP-10G-D-CAB-5M-Z	R7743P05
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-GE-LH100-SM1550	R7743P05
		SFP-GE-LH40-SM1310	R7743P05
		SFP-GE-LH40-SM1310-BIDI	R7743P05
		SFP-GE-LH40-SM1310-D	R7743P05
		SFP-GE-LH40-SM1550	R7743P05
		SFP-GE-LH40-SM1550-BIDI	R7743P05
		SFP-GE-LH70-SM1490-BIDI	R7743P05
		SFP-GE-LH70-SM1550-BIDI	R7743P05
		SFP-GE-LH80-SM1550	R7743P05
		SFP-GE-LH80-SM1550-D	R7743P05
		SFP-GE-LX-SM1310-A	R7743P05
		SFP-GE-LX-SM1310-A-Z	R7743P05
		SFP-GE-LX-SM1310-BIDI	R7743P05
		SFP-GE-LX-SM1310-D	R7743P05
		SFP-GE-LX-SM1490-BIDI	R7743P05
		SFP-GE-SX-MM850-A	R7743P05
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P05

单板名称	端口	支持的光模块	说明
		SFP-GE-SX-MM850-D	R7743P05
		SFP-GE-T	R7743P05
		SFP-GE-T-D	R7743P05
		SFP-GE-T-Z	R7743P05
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	R7743P05
		SFP-XG-LH40-SM1330-BIDI	R7743P05
		SFP-XG-LH40-SM1550	R7743P05
		SFP-XG-LH40-SM1550-D	R7743P05
		SFP-XG-LH40-SM1550-Z	R7743P05
		SFP-XG-LH80-SM1490-BIDI	R7743P05
		SFP-XG-LH80-SM1550	R7743P05
		SFP-XG-LH80-SM1550-BIDI	R7743P05
		SFP-XG-LH80-SM1550-D	R7743P05
		SFP-XG-LX-SM1270-BIDI	R7743P05
		SFP-XG-LX-SM1310	R7743P05
		SFP-XG-LX-SM1310-D	R7743P05
		SFP-XG-LX-SM1310-E	R7743P05
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7743P05
		SFP-XG-LX-SM1330-BIDI	R7743P05
		SFP-XG-SX-MM850-A	R7743P05
		SFP-XG-SX-MM850-D	R7743P05
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7743P05
		SFP-XG-SX-MM850-E	R7743P05
		SFP-XG-SX-MM850-H	E7755
LSCM3CGS8QS8SF0-Z	1~4, 13~16	LSWM1QSTK0	R7753P08

单板名称	端口	支持的光模块	说明
		LSWM1QSTK1	R7753P08
		LSWM1QSTK2	R7753P08
		LSWM1QSTK3	R7753P08
		LSWM1QSTK4	R7753P08
		LSWM1QSTK5	R7753P08
		QSFP-40G-4SFP-10G-CAB-1M-Z	R7753P08
		QSFP-40G-4SFP-10G-CAB-3M-Z	R7753P08
		QSFP-40G-4SFP-10G-CAB-5M-Z	R7753P08
		QSFP-40G-BIDI-SR-MM850	R7753P08
		QSFP-40G-BIDI-SR-MM850-Z	R7753P08
		QSFP-40G-BIDI-WDM850	R7753P08
		QSFP-40G-CSR4-MM850	R7753P08
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	R7753P08
		QSFP-40G-D-AOC-10M	R7753P08
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	R7753P08
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	R7753P08
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-D-CAB-1M-Z	R7753P08
		QSFP-40G-D-CAB-3M-Z	R7753P08
		QSFP-40G-D-CAB-5M-Z	R7753P08
		QSFP-40G-ER4-WDM1300	R7753P08
		QSFP-40G-ER4-WDM1300-Z	R7753P08
		QSFP-40G-LR4L-WDM1300	R7753P08
		QSFP-40G-LR4L-WDM1300-Z	R7753P08
		QSFP-40G-LR4-PSM1310	R7753P08
		QSFP-40G-LR4-WDM1300	R7753P08
		QSFP-40G-LR4-WDM1300-Z	R7753P08
		QSFP-40G-SR4-MM850	R7753P08
		QSFP-40G-SR4-MM850-H	E7755

单板名称	端口	支持的光模块	说明
	5~12	QSFP-40G-SR4-MM850-Z	R7753P08
		LSWM1QSTK0	R7753P08
		LSWM1QSTK1	R7753P08
		LSWM1QSTK2	R7753P08
		LSWM1QSTK3	R7753P08
		LSWM1QSTK4	R7753P08
		LSWM1QSTK5	R7753P08
		QSFP-100G-4SFP-25G-CAB-1M	R7755P03
		QSFP-100G-4SFP-25G-CAB-1M-Z	R7755P03
		QSFP-100G-4SFP-25G-CAB-3M	R7753P08
		QSFP-100G-4SFP-25G-CAB-3M-Z	R7753P08
		QSFP-100G-BIDI-MM850	R7756P07
		QSFP-100G-BIDI-MM850-Z	R7756P07
		QSFP-100G-CWDM4-SM1300-A	R7753P08
		QSFP-100G-D-AOC-10M	R7753P08
		QSFP-100G-D-AOC-10M-H	E7755
		QSFP-100G-D-AOC-20M	R7753P08
		QSFP-100G-D-AOC-20M-H	E7755
		QSFP-100G-D-AOC-7M	R7753P08
		QSFP-100G-D-AOC-7M-H	E7755
		QSFP-100G-D-CAB-1M	R7753P08
		QSFP-100G-D-CAB-1M-Z	R7753P08
		QSFP-100G-D-CAB-3M	R7753P08
		QSFP-100G-D-CAB-3M-Z	R7753P08
		QSFP-100G-eSR4-MM850	R7753P08
		QSFP-100G-LR4L-WDM1300	R7753P08
		QSFP-100G-LR4L-WDM1300-Z	R7753P08
		QSFP-100G-LR4-WDM1300	R7753P08
		QSFP-100G-LR4-WDM1300-A	R7753P08
		QSFP-100G-LR4-WDM1300-Z	R7753P08
		QSFP-100G-PSM4-SM1310	R7753P08
		QSFP-100G-SR4-MM850	R7753P08

单板名称	端口	支持的光模块	说明
		QSFP-100G-SR4-MM850-A	R7753P08
		QSFP-100G-SR4-MM850-H	E7755
		QSFP-100G-SR4-MM850-Z	R7753P08
		QSFP-100G-SWDM4-MM850	R7753P08
		QSFP-100G-SWDM4-MM850-Z	R7753P08
		QSFP-40G-4SFP-10G-CAB-1M-Z	R7753P08
		QSFP-40G-4SFP-10G-CAB-3M-Z	R7753P08
		QSFP-40G-4SFP-10G-CAB-5M-Z	R7753P08
		QSFP-40G-BIDI-SR-MM850	R7753P08
		QSFP-40G-BIDI-SR-MM850-Z	R7753P08
		QSFP-40G-BIDI-WDM850	R7753P08
		QSFP-40G-CSR4-MM850	R7753P08
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	R7753P08
		QSFP-40G-D-AOC-10M	R7753P08
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	R7753P08
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	R7753P08
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-D-CAB-1M-Z	R7753P08
		QSFP-40G-D-CAB-3M-Z	R7753P08
		QSFP-40G-D-CAB-5M-Z	R7753P08
		QSFP-40G-ER4-WDM1300	R7753P08
		QSFP-40G-ER4-WDM1300-Z	R7753P08
		QSFP-40G-LR4L-WDM1300	R7753P08
		QSFP-40G-LR4L-WDM1300-Z	R7753P08
		QSFP-40G-LR4-PSM1310	R7753P08
		QSFP-40G-LR4-WDM1300	R7753P08
		QSFP-40G-LR4-WDM1300-Z	R7753P08
		QSFP-40G-SR4-MM850	R7753P08
		QSFP-40G-SR4-MM850-H	E7755

单板名称	端口	支持的光模块	说明
		QSFP-40G-SR4-MM850-Z	R7753P08
LSCM3MPUS06A0-Z	1	SFP-GE-LH100-SM1550	R7743
		SFP-GE-LH40-SM1310	R7743
		SFP-GE-LH40-SM1310-D	R7743
		SFP-GE-LH40-SM1550	R7743
		SFP-GE-LH80-SM1550	R7743
		SFP-GE-LH80-SM1550-D	R7743
		SFP-GE-LX-SM1310-A	R7743
		SFP-GE-LX-SM1310-A-Z	R7743
		SFP-GE-LX-SM1310-BIDI	R7743
		SFP-GE-LX-SM1310-D	R7743
		SFP-GE-LX-SM1490-BIDI	R7743
		SFP-GE-SX-MM850-A	R7743
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743
		SFP-GE-SX-MM850-D	R7743
LSCM3MPUS10B0-Z	MANAGEMENT	SFP-GE-LH100-SM1550	E7744P07
		SFP-GE-LH40-SM1310	E7744P07
		SFP-GE-LH40-SM1310-D	E7744P07
		SFP-GE-LH40-SM1550	E7744P07
		SFP-GE-LH80-SM1550	E7744P07
		SFP-GE-LH80-SM1550-D	E7744P07
		SFP-GE-LX-SM1310-A	E7744P07
		SFP-GE-LX-SM1310-A-Z	E7744P07
		SFP-GE-LX-SM1310-BIDI	E7744P07
		SFP-GE-LX-SM1310-D	E7744P07
		SFP-GE-LX-SM1490-BIDI	E7744P07
		SFP-GE-SX-MM850-A	E7744P07
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7744P07

单板名称	端口	支持的光模块	说明
		SFP-GE-SX-MM850-D	E7744P07
LSCM3QGS8CSSE0-Z	1~4,9~12,5~8	LSWM1QSTK0	R7743,Can only be used for IRF/M-LAG setup connections.
		LSWM1QSTK1	R7743,Can only be used for IRF/M-LAG setup connections.
		LSWM1QSTK2	R7743,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-BIDI-SR-MM850	R7743
		QSFP-40G-BIDI-SR-MM850-Z	R7743
		QSFP-40G-BIDI-WDM850	R7743
		QSFP-40G-CSR4-MM850	R7743
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	R7743
		QSFP-40G-D-AOC-10M	R7743
		QSFP-40G-D-AOC-10M-H	E7755
		QSFP-40G-D-AOC-20M	R7743
		QSFP-40G-D-AOC-20M-H	E7755
		QSFP-40G-D-AOC-7M	R7743
		QSFP-40G-D-AOC-7M-H	E7755
		QSFP-40G-D-CAB-1M-Z	R7743P05 ,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-D-CAB-3M-Z	R7743P05 ,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-D-CAB-5M-Z	R7743P05 ,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-ER4-WDM1300	R7743
		QSFP-40G-ER4-WDM1300-Z	R7743
		QSFP-40G-LR4L-WDM1300	R7743
		QSFP-40G-LR4L-WDM1300-Z	R7743
		QSFP-40G-LR4-WDM1300	R7743
		QSFP-40G-LR4-WDM1300-Z	R7743

单板名称	端口	支持的光模块	说明
		QSFP-40G-SR4-MM850	R7743
		QSFP-40G-SR4-MM850-H	E7755
		QSFP-40G-SR4-MM850-Z	R7743
	5~8	QSFP-100G-CWDM4-SM1300-A	R7743
		QSFP-100G-D-AOC-10M	E775304
		QSFP-100G-D-AOC-10M-H	E7755
		QSFP-100G-D-AOC-20M	E775304
		QSFP-100G-D-AOC-20M-H	E7755
		QSFP-100G-D-AOC-7M	R7743
		QSFP-100G-D-AOC-7M-H	E7755
		QSFP-100G-ER4L-WDM1300	R7743
		QSFP-100G-ER4L-WDM1300-Z	R7743
		QSFP-100G-eSR4-MM850	R7743
		QSFP-100G-LR4L-WDM1300	R7743
		QSFP-100G-LR4L-WDM1300-Z	R7743
		QSFP-100G-LR4-WDM1300	R7743
		QSFP-100G-LR4-WDM1300-Z	R7743
		QSFP-100G-PSM4-SM1310	R7743
		QSFP-100G-SR4-MM850	R7743
		QSFP-100G-SR4-MM850-A	R7743
		QSFP-100G-SR4-MM850-H	E7755
		QSFP-100G-SR4-MM850-Z	R7743
		QSFP-100G-SWDM4-MM850	R7743
		QSFP-100G-SWDM4-MM850-Z	R7743
LSCM3QGS8CSSE0-ZE	1~4,9~12,5~8	LSWM1QSTK0	R7743P07,Can only be used for IRF/M-LAG setup connections.
		LSWM1QSTK1	R7743P07,Can only be used for IRF/M-LAG setup connections.
		LSWM1QSTK2	R7743P07,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-BIDI-SR-MM850	R7743P07

单板名称	端口	支持的光模块	说明
		QSFP-40G-BIDI-SR-MM850-Z	R7743P07
		QSFP-40G-BIDI-WDM850	R7743P07
		QSFP-40G-CSR4-MM850	R7743P07
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	R7743P07
		QSFP-40G-D-AOC-10M	R7743P07
		QSFP-40G-D-AOC-10M-H	E7755
		QSFP-40G-D-AOC-20M	R7743P07
		QSFP-40G-D-AOC-20M-H	E7755
		QSFP-40G-D-AOC-7M	R7743P07
		QSFP-40G-D-AOC-7M-H	E7755
		QSFP-40G-D-CAB-1M-Z	R7743P07,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-D-CAB-3M-Z	R7743P07,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-D-CAB-5M-Z	R7743P07,Can only be used for IRF/M-LAG setup connections.
		QSFP-40G-ER4-WDM1300	R7743P07
		QSFP-40G-ER4-WDM1300-Z	R7743P07
		QSFP-40G-LR4L-WDM1300	R7743P07
		QSFP-40G-LR4L-WDM1300-Z	R7743P07
		QSFP-40G-LR4-WDM1300	R7743P07
		QSFP-40G-LR4-WDM1300-Z	R7743P07
		QSFP-40G-SR4-MM850	R7743P07
		QSFP-40G-SR4-MM850-H	E7755
		QSFP-40G-SR4-MM850-Z	R7743P07
	5~8	QSFP-100G-CWDM4-SM1300-A	R7743P07
		QSFP-100G-D-AOC-10M	E775304
		QSFP-100G-D-AOC-10M-H	E7755
		QSFP-100G-D-AOC-20M	E775304
		QSFP-100G-D-AOC-20M-H	E7755
		QSFP-100G-D-AOC-7M	R7743P07

单板名称	端口	支持的光模块	说明
		QSFP-100G-D-AOC-7M-H	E7755
		QSFP-100G-ER4L-WDM1300	R7743P07
		QSFP-100G-ER4L-WDM1300-Z	R7743P07
		QSFP-100G-eSR4-MM850	R7743P07
		QSFP-100G-LR4L-WDM1300	R7743P07
		QSFP-100G-LR4L-WDM1300-Z	R7743P07
		QSFP-100G-LR4-WDM1300	R7743P07
		QSFP-100G-LR4-WDM1300-Z	R7743P07
		QSFP-100G-PSM4-SM1310	R7743P07
		QSFP-100G-SR4-MM850	R7743P07
		QSFP-100G-SR4-MM850-A	R7743P07
		QSFP-100G-SR4-MM850-H	E7755
		QSFP-100G-SR4-MM850-Z	R7743P07
		QSFP-100G-SWDM4-MM850	R7743P07
		QSFP-100G-SWDM4-MM850-Z	R7743P07
LSCM3SRP6C4Y06A0-Z	1~6	LSWM1QSTK0	R7753P08
		LSWM1QSTK1	R7753P08
		LSWM1QSTK2	R7753P08
		LSWM1QSTK3	R7753P08
		LSWM1QSTK4	R7753P08
		LSWM1QSTK5	R7753P08
		QSFP-100G-4SFP-25G-CAB-1M	R7753P08
		QSFP-100G-4SFP-25G-CAB-1M-Z	R7753P08
		QSFP-100G-BIDI-MM850	R7756P07
		QSFP-100G-BIDI-MM850-Z	R7756P07
		QSFP-100G-CWDM4-SM1300-A	R7753P08
		QSFP-100G-D-AOC-10M	R7753P08
		QSFP-100G-D-AOC-10M-H	E7755
		QSFP-100G-D-AOC-10M-Z	R7753P08
		QSFP-100G-D-AOC-20M	R7753P08
		QSFP-100G-D-AOC-20M-H	E7755
		QSFP-100G-D-AOC-7M	R7753P08

单板名称	端口	支持的光模块	说明
		QSFP-100G-D-AOC-7M-H	E7755
		QSFP-100G-D-CAB-1M	R7753P08
		QSFP-100G-D-CAB-1M-Z	R7753P08
		QSFP-100G-eSR4-MM850	R7753P08
		QSFP-100G-LR4L-WDM1300	R7753P08
		QSFP-100G-LR4L-WDM1300-Z	R7753P08
		QSFP-100G-LR4-WDM1300	R7753P08
		QSFP-100G-LR4-WDM1300-A	R7753P08
		QSFP-100G-LR4-WDM1300-Z	R7753P08
		QSFP-100G-PSM4-SM1310	R7753P08
		QSFP-100G-SR4-MM850	R7753P08
		QSFP-100G-SR4-MM850-A	R7753P08
		QSFP-100G-SR4-MM850-H	E7755
		QSFP-100G-SR4-MM850-Z	R7753P08
		QSFP-100G-SWDM4-MM850	R7753P08
		QSFP-100G-SWDM4-MM850-Z	R7753P08
		QSFP-40G-4SFP-10G-CAB-1M-Z	R7753P08
		QSFP-40G-4SFP-10G-CAB-3M-Z	R7753P08
		QSFP-40G-4SFP-10G-CAB-5M-Z	R7753P08
		QSFP-40G-BIDI-SR-MM850	R7753P08
		QSFP-40G-BIDI-SR-MM850-Z	R7753P08
		QSFP-40G-BIDI-WDM850	R7753P08
		QSFP-40G-CSR4-MM850	R7753P08
		QSFP-40G-CSR4-MM850-H	E7755
		QSFP-40G-CSR4-MM850-Z	R7753P08
		QSFP-40G-D-AOC-10M	R7753P08
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	R7753P08
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	R7753P08
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-D-CAB-1M-Z	R7753P08

单板名称	端口	支持的光模块	说明
		QSFP-40G-D-CAB-3M-Z	R7753P08
		QSFP-40G-D-CAB-5M-Z	R7753P08
		QSFP-40G-ER4-WDM1300	R7753P08
		QSFP-40G-ER4-WDM1300-Z	R7753P08
		QSFP-40G-LR4L-WDM1300	R7753P08
		QSFP-40G-LR4L-WDM1300-Z	R7753P08
		QSFP-40G-LR4-PSM1310	R7753P08
		QSFP-40G-LR4-WDM1300	R7753P08
		QSFP-40G-LR4-WDM1300-Z	R7753P08
		QSFP-40G-SR4-MM850	R7753P08
		QSFP-40G-SR4-MM850-H	E7755
		QSFP-40G-SR4-MM850-Z	R7753P08
	7~10	CAB-0.5M-SFP+	R7753P08
		CAB-1M-SFP+	R7753P08
		CAB-3M-SFP+	R7753P08
		LSTM1STK	R7753P08
		LSWM1STK	R7753P08
		LSWM2STK	R7753P08
		LSWM3STK	R7753P08
		SFP-10G-D-CAB-1M-Z	R7753P08
		SFP-10G-D-CAB-3M-Z	R7753P08
		SFP-10G-D-CAB-5M-Z	R7753P08
		SFP-25G-CSR-MM850	R7755P03
		SFP-25G-D-AOC-10M	E7753P06
		SFP-25G-D-AOC-10M-H	E7755
		SFP-25G-D-AOC-20M	E7753P06
		SFP-25G-D-AOC-20M-H	E7755
		SFP-25G-D-AOC-3M	R7753P08
		SFP-25G-D-AOC-5M	R7753P08
		SFP-25G-D-AOC-5M-H	E7755
		SFP-25G-D-AOC-7M	E7753P06
		SFP-25G-D-AOC-7M-H	E7755

单板名称	端口	支持的光模块	说明
		SFP-25G-D-CAB-1M	R7753P08
		SFP-25G-LR-SM1310	R7753P08
		SFP-25G-LR-SM1310-Z	R7753P08
		SFP-25G-SR-MM850	R7753P08
		SFP-25G-SR-MM850-H	E7755
		SFP-25G-SR-MM850-Z	R7753P08
		SFP-GE-LH100-SM1550	R7753P08
		SFP-GE-LH40-SM1310	R7753P08
		SFP-GE-LH40-SM1310-A-Z	R7753P08
		SFP-GE-LH40-SM1310-BIDI	R7753P08
		SFP-GE-LH40-SM1310-D	R7753P08
		SFP-GE-LH40-SM1550	R7753P08
		SFP-GE-LH40-SM1550-BIDI	R7753P08
		SFP-GE-LH70-SM1490-BIDI	R7753P08
		SFP-GE-LH70-SM1550-BIDI	R7753P08
		SFP-GE-LH80-SM1550	R7753P08
		SFP-GE-LH80-SM1550-D	R7753P08
		SFP-GE-LH80-SM1550-Z	R7753P08
		SFP-GE-LX-SM1310-A	R7753P08
		SFP-GE-LX-SM1310-A-Z	R7753P08
		SFP-GE-LX-SM1310-BIDI	R7753P08
		SFP-GE-LX-SM1310-D	R7753P08
		SFP-GE-LX-SM1310-S	R7753P08
		SFP-GE-LX-SM1490-BIDI	R7753P08
		SFP-GE-SX-MM850-A	R7753P08
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7753P08
		SFP-GE-SX-MM850-D	R7753P08
		SFP-GE-SX-MM850-S	R7753P08
		SFP-GE-T	R7753P08
		SFP-GE-T-D	R7753P08

单板名称	端口	支持的光模块	说明
		SFP-GE-T-Z	R7753P08
		SFP-XG-D-AOC-10M-H	E7755
		SFP-XG-D-AOC-20M-H	E7755
		SFP-XG-D-AOC-7M-H	E7755
		SFP-XG-LH40-SM1270-BIDI	R7753P08
		SFP-XG-LH40-SM1330-BIDI	R7753P08
		SFP-XG-LH40-SM1550	R7753P08
		SFP-XG-LH40-SM1550-D	R7753P08
		SFP-XG-LH40-SM1550-Z	R7753P08
		SFP-XG-LH80-SM1490-BIDI	R7753P08
		SFP-XG-LH80-SM1550	R7753P08
		SFP-XG-LH80-SM1550-A-Z	R7753P08
		SFP-XG-LH80-SM1550-BIDI	R7753P08
		SFP-XG-LH80-SM1550-D	R7753P08
		SFP-XG-LX-SM1270-BIDI	R7753P08
		SFP-XG-LX-SM1310	R7753P08
		SFP-XG-LX-SM1310-D	R7753P08
		SFP-XG-LX-SM1310-E	R7753P08
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7753P08
		SFP-XG-LX-SM1310-S	R7753P08
		SFP-XG-LX-SM1330-BIDI	R7753P08
		SFP-XG-SX-MM850-A	R7753P08
		SFP-XG-SX-MM850-D	R7753P08
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7753P08
		SFP-XG-SX-MM850-E	R7753P08
		SFP-XG-SX-MM850-H	E7755
		SFP-XG-SX-MM850-S	R7753P08
	MANAGEMENT	SFP-GE-LH100-SM1550	R7753P08

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1310	R7753P08
		SFP-GE-LH40-SM1310-A-Z	R7753P08
		SFP-GE-LH40-SM1310-D	R7753P08
		SFP-GE-LH40-SM1550	R7753P08
		SFP-GE-LH80-SM1550	R7753P08
		SFP-GE-LH80-SM1550-D	R7753P08
		SFP-GE-LH80-SM1550-Z	R7753P08
		SFP-GE-LX-SM1310-A	R7753P08
		SFP-GE-LX-SM1310-A-Z	R7753P08
		SFP-GE-LX-SM1310-BIDI	R7753P08
		SFP-GE-LX-SM1310-D	R7753P08
		SFP-GE-LX-SM1490-BIDI	R7753P08
		SFP-GE-SX-MM850-A	R7753P08
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7753P08
		SFP-GE-SX-MM850-D	R7753P08
LSCM3SUP03A0-Z	1	SFP-GE-LH100-SM1550	R7743
		SFP-GE-LH40-SM1310	R7743
		SFP-GE-LH40-SM1310-D	R7743
		SFP-GE-LH40-SM1550	R7743
		SFP-GE-LH80-SM1550	R7743
		SFP-GE-LH80-SM1550-D	R7743
		SFP-GE-LX-SM1310-A	R7743
		SFP-GE-LX-SM1310-A-Z	R7743
		SFP-GE-LX-SM1310-BIDI	R7743
		SFP-GE-LX-SM1310-D	R7743
		SFP-GE-LX-SM1490-BIDI	R7743
		SFP-GE-SX-MM850-A	R7743
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743

单板名称	端口	支持的光模块	说明
LSCM3SUP03A0-ZE	1	SFP-GE-SX-MM850-D	R7743
		SFP-GE-LH100-SM1550	R7743P07
		SFP-GE-LH40-SM1310	R7743P07
		SFP-GE-LH40-SM1310-D	R7743P07
		SFP-GE-LH40-SM1550	R7743P07
		SFP-GE-LH80-SM1550	R7743P07
		SFP-GE-LH80-SM1550-D	R7743P07
		SFP-GE-LX-SM1310-A	R7743P07
		SFP-GE-LX-SM1310-A-Z	R7743P07
		SFP-GE-LX-SM1310-BIDI	R7743P07
		SFP-GE-LX-SM1310-D	R7743P07
		SFP-GE-LX-SM1490-BIDI	R7743P07
		SFP-GE-SX-MM850-A	R7743P07
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P07
		SFP-GE-SX-MM850-D	R7743P07
LSCM3TGS48SE0-Z	1~48	CAB-0.5M-SFP+	R7743
		CAB-1M-SFP+	R7743
		CAB-3M-SFP+	R7743
		LSTM1STK	R7743
		LSWM1STK	R7743
		LSWM2STK	R7743
		LSWM3STK	R7743
		SFP-10G-D-CAB-1M-Z	R7743P05
		SFP-10G-D-CAB-3M-Z	R7743P05
		SFP-10G-D-CAB-5M-Z	R7743P05
		SFP-2.5G-LX10-SM1310-DR-I	E7756P01
		SFP-GE-LH100-SM1550	R7743
		SFP-GE-LH40-SM1310	R7743
		SFP-GE-LH40-SM1310-D	R7743
		SFP-GE-LH40-SM1550	R7743

单板名称	端口	支持的光模块	说明
		SFP-GE-LH80-SM1550	R7743
		SFP-GE-LH80-SM1550-D	R7743
		SFP-GE-LX-SM1310-A	R7743
		SFP-GE-LX-SM1310-A-Z	R7743
		SFP-GE-LX-SM1310-BIDI	R7743
		SFP-GE-LX-SM1310-D	R7743
		SFP-GE-LX-SM1490-BIDI	R7743
		SFP-GE-SX-MM850-A	R7743
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743
		SFP-GE-SX-MM850-D	R7743
		SFP-GE-T	R7743
		SFP-GE-T-D	R7743
		SFP-GE-T-Z	R7743
		SFP-XG-LH40-SM1550	R7743
		SFP-XG-LH40-SM1550-D	R7743
		SFP-XG-LH40-SM1550-Z	R7743
		SFP-XG-LH80-SM1550	R7743
		SFP-XG-LH80-SM1550-D	R7743
		SFP-XG-LX-SM1310	R7743
		SFP-XG-LX-SM1310-D	R7743
		SFP-XG-LX-SM1310-E	R7743
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7743
		SFP-XG-SX-MM850-A	R7743
		SFP-XG-SX-MM850-D	R7743
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7743
		SFP-XG-SX-MM850-E	R7743

单板名称	端口	支持的光模块	说明
LSCM3TGS48SE0-ZE	1~48	SFP-XG-SX-MM850-F1	R7743
		SFP-XG-SX-MM850-H	E7755
		CAB-0.5M-SFP+	R7743P07
		CAB-1M-SFP+	R7743P07
		CAB-3M-SFP+	R7743P07
		LSTM1STK	R7743P07
		LSWM1STK	R7743P07
		LSWM2STK	R7743P07
		LSWM3STK	R7743P07
		SFP-10G-D-CAB-1M-Z	R7743P07
		SFP-10G-D-CAB-3M-Z	R7743P07
		SFP-10G-D-CAB-5M-Z	R7743P07
		SFP-2.5G-LX10-SM1310-DR-I	E7756P01
		SFP-GE-LH100-SM1550	R7743P07
		SFP-GE-LH40-SM1310	R7743P07
		SFP-GE-LH40-SM1310-D	R7743P07
		SFP-GE-LH40-SM1550	R7743P07
		SFP-GE-LH80-SM1550	R7743P07
		SFP-GE-LH80-SM1550-D	R7743P07
		SFP-GE-LX-SM1310-A	R7743P07
		SFP-GE-LX-SM1310-A-Z	R7743P07
		SFP-GE-LX-SM1310-BIDI	R7743P07
		SFP-GE-LX-SM1310-D	R7743P07
		SFP-GE-LX-SM1490-BIDI	R7743P07
		SFP-GE-SX-MM850-A	R7743P07
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7743P07
		SFP-GE-SX-MM850-D	R7743P07
		SFP-GE-T	R7743P07
		SFP-GE-T-D	R7743P07
		SFP-GE-T-Z	R7743P07

单板名称	端口	支持的光模块	说明
		SFP-XG-LH40-SM1550	R7743P07
		SFP-XG-LH40-SM1550-D	R7743P07
		SFP-XG-LH40-SM1550-Z	R7743P07
		SFP-XG-LH80-SM1550	R7743P07
		SFP-XG-LH80-SM1550-D	R7743P07
		SFP-XG-LX-SM1310	R7743P07
		SFP-XG-LX-SM1310-D	R7743P07
		SFP-XG-LX-SM1310-E	R7743P07
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7743P07
		SFP-XG-SX-MM850-A	R7743P07
		SFP-XG-SX-MM850-D	R7743P07
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7743P07
		SFP-XG-SX-MM850-E	R7743P07
		SFP-XG-SX-MM850-F1	R7743P07
		SFP-XG-SX-MM850-H	E7755
LSCM3TGS48SF0-Z	1~48	CAB-0.5M-SFP+	R7753P08
		CAB-1M-SFP+	R7753P08
		CAB-3M-SFP+	R7753P08
		LSTM1STK	R7753P08
		LSWM1STK	R7753P08
		LSWM2STK	R7753P08
		LSWM3STK	R7753P08
		SFP-10G-D-CAB-1M-Z	R7753P08
		SFP-10G-D-CAB-3M-Z	R7753P08
		SFP-10G-D-CAB-5M-Z	R7753P08
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-GE-LH100-SM1550	R7753P08
		SFP-GE-LH40-SM1310	R7753P08

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1310-A-Z	R7753P08
		SFP-GE-LH40-SM1310-BIDI	R7753P08
		SFP-GE-LH40-SM1310-D	R7753P08
		SFP-GE-LH40-SM1550	R7753P08
		SFP-GE-LH40-SM1550-BIDI	R7753P08
		SFP-GE-LH70-SM1490-BIDI	R7753P08
		SFP-GE-LH70-SM1550-BIDI	R7753P08
		SFP-GE-LH80-SM1550	R7753P08
		SFP-GE-LH80-SM1550-D	R7753P08
		SFP-GE-LH80-SM1550-Z	R7753P08
		SFP-GE-LX-SM1310-A	R7753P08
		SFP-GE-LX-SM1310-A-Z	R7753P08
		SFP-GE-LX-SM1310-BIDI	R7753P08
		SFP-GE-LX-SM1310-D	R7753P08
		SFP-GE-LX-SM1310-S	R7753P08
		SFP-GE-LX-SM1490-BIDI	R7753P08
		SFP-GE-SX-MM850-A	R7753P08
		SFP-GE-SX-MM850-A-H-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	E7756P02
		SFP-GE-SX-MM850-A-Z	R7753P08
		SFP-GE-SX-MM850-D	R7753P08
		SFP-GE-SX-MM850-S	R7753P08
		SFP-GE-T	R7753P08
		SFP-GE-T-D	R7753P08
		SFP-GE-T-Z	R7753P08
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	R7753P08
		SFP-XG-LH40-SM1330-BIDI	R7753P08
		SFP-XG-LH40-SM1550	R7753P08
		SFP-XG-LH40-SM1550-D	R7753P08

单板名称	端口	支持的光模块	说明
		SFP-XG-LH40-SM1550-Z	R7753P08
		SFP-XG-LH80-SM1550	R7753P08
		SFP-XG-LH80-SM1550-A-Z	R7753P08
		SFP-XG-LH80-SM1550-D	R7753P08
		SFP-XG-LX-SM1270-BIDI	R7753P08
		SFP-XG-LX-SM1310	R7753P08
		SFP-XG-LX-SM1310-D	R7753P08
		SFP-XG-LX-SM1310-E	R7753P08
		SFP-XG-LX-SM1310-E-H-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	E7756P02
		SFP-XG-LX-SM1310-E-Z	R7753P08
		SFP-XG-LX-SM1310-S	R7753P08
		SFP-XG-LX-SM1330-BIDI	R7753P08
		SFP-XG-SX-MM850-A	R7753P08
		SFP-XG-SX-MM850-D	R7753P08
		SFP-XG-SX-MM850-D-H-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	E7756P02
		SFP-XG-SX-MM850-D-Z	R7753P08
		SFP-XG-SX-MM850-E	R7753P08
		SFP-XG-SX-MM850-H	E7755
		SFP-XG-SX-MM850-S	R7753P08